


DRAWING NO.	FEATURE
171651-01	-----
171651-11	1B1 12D
171651-12	1B1 78J
171651-15	265 12D
171651-16	265 78J

RELEASE	REV DATE	DWG NO	171651
REV ZONE	REVISION RECORD	DATE	DFT-ORIG



- NOTES:
- ALL WIRES TO BE SECURED WITH CLAMP 010495-01-000 OR CLIP 080734-01-000 EVERY 600MM. USE SCREW 000G67-10-12B UNLESS OTHERWISE SPECIFIED.
 - ALL 110V WIRE TO BE CLAMPED WITH CLAMP 010497-05-000 WITHIN 200MM OF OUTLET BOXES, USE SCREW 000G67-10-12B.
 - ALL GROUND WIRE TO BE COVERED WITH TUBING 008041-02-000.
 - SEE WIRING DIAGRAM-BODY, 110V FOR ADDITIONAL INFORMATION.
- 8 MOUNT ATS AS HIGH AS POSSIBLE IN COMPARTMENT. ROUTE GROUND CABLE WITH GENERATOR WIRES THROUGH PANEL & CONNECT TO FRAME RAIL GROUND.
- 7 MOUNT 4X4 BOX ON CLOSEOUT PANEL OVER HOLE.
- 6 WIRE PASSES THROUGH FLOOR AT THIS POINT.
- 5 SEE LOAD CENTER/ATS ASM FOR ADDITIONAL INFORMATION.

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

- 12D ELECTRICAL SYSTEM 30 AMP
- 40D INVERTER-DC/AC, 400 WATT
- 40A INVERTER-DC/AC WITHOUT
- 78J ELECTRICAL SYSTEM-50 AMP
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

WINNEBAGO INDUSTRIES		COPYRIGHT 2010 WINNEBAGO INDUSTRIES, INC.	
DFT-ORIG	ORIG. DATE	ALL DIMENSIONS ARE IN MILLIMETERS	
CHK-OR		10 J32H	
P.E.		FIRST USED	
M.E.			
DSNR			
UNSPECIFIED TOLERANCES ARE:		MATERIAL:	
WHOLE DIM (X)	± 3		
ONE-PLACE (X.X)	± 1.5		
TWO-PLACE (X.XX)	± 0.50		
ANGLE	± 1°		
THIRD ANGLE PROJECTION			
DO NOT SCALE DRAWING			
TITLE: WIRING INSTL-BODY, 110V			
SHEET 1 OF 6	PART NO 171651	REV	

TV-19",LCD
170909-01-000
TV-19" AC POWER SUPPLY
170909-04-000
CABLE ASM-COAX
087105-01-006

SLIDEOUT ROOF

SCREW
0MG02B-04-012 (4)
WASHER
000E14-10-00B (4)
USED TO MOUNT TV,
TO TV BRACKET
SCREW
000G39-10-12B (6)
BRACKET TO SLIDE
END WALL

BRACKET-MOUNT,TV
162393-01-04B
PLATE-MOUNT,TV
162394-03-04B
BOLT
000C12-04-10B (3)
NUT
000D39-04-00B (3)

RECEPTACLE-GFI, 15A 125V
163319-01-02A
BOX
133070-01-000
133070-02-000
SCREW
000G13-07-12B(4)

RECEPTACLE-SINGLE
172839-02-01A (UP TO 01-24-10)
RECEPTACLE-SINGLE, FLUSH MOUNT
176149-02-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

RECEPTACLE-SINGLE, SURFACE MOUNT
058707-01-000 (UP TO 01-24-10)
RECEPTACLE-SINGLE, SURFACE MOUNT
176156-01-01A (AFTER 01-25-10)

RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

RECEPTACLE-SINGLE, SURFACE MOUNT
058707-01-000 (UP TO 01-24-10)
RECEPTACLE-SINGLE, SURFACE MOUNT
176156-01-01A (AFTER 01-25-10)

22B OR 22F

RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

(BRN ENDS AT GALLEY
GFI WITHOUT 22B OR 22F)

ROUTE 110V WIRES
WITH DRAINAGE PIPES

GALLEY SLIDEOUT
110V CONNECTIONS
DETAIL FA

BRACKET
155223-02-02B
SCREW
000G67-10-08B (3)

LOOP BROWN CIRCUIT UP
1200MM FROM FLOOR

REF FLOOR

DETAIL BA

X-X

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

8 CLEAN AND APPLY ADHESIVE PROMOTER 900680-04-000
TO BOTH SURFACES AND BOND WITH TAPE 076322-23-000
(900MM) AROUND ENTIRE PERIMETER OF BRACKET

7 LOCATING DIMENSION SEE DETAIL BA

6 WIRE ROUTED THROUGH FLOOR AT THIS POINT.

5 SEE LOAD CENTER/ATS ASM FOR ADDITIONAL INFORMATION.

4. SEE WIRING DIAGRAM-BODY,110V FOR ADDITIONAL INFORMATION.

3. ALL GROUND WIRE TO BE COVERED WITH TUBING 008041-02-000.

2. ALL 110V WIRE TO BE CLAMPED WITH CLAMP 010497-05-000
WITHIN 200MM OF OUTLET BOXES, USE SCREW 000G67-10-12B.

1. ALL WIRES TO BE SECURED WITH CLAMP 010495-01-000
OR CLIP 080734-01-000 EVERY 600MM. USE SCREW
000G67-10-12B UNLESS OTHERWISE SPECIFIED.

NOTES:

12D ELECTRICAL SYSTEM 30 AMP
22F DINETTE, U-SHAPED ULTRALEATH
22B DINETTE - U-SHAPED
78J ELECTRICAL SYSTEM-50 AMP
265 CODES/STANDARDS-CSA/CMVSS
1B1 CODES/STANDARDS USA

1B1 265 78J 12D

FIRST USED

10 J32H

DO NOT SCALE DRAWING

TITLE:


WIRING INSTL-BODY,110V

SHEET 2

PART NO

171651

REV



- 10 SEE WIRING INSTL-TV/DVD FOR ADDITIONAL INFORMATION.
- 9 SEE VIEW DB FOR POSITIONING.
- 8 WIRE IN ROOF.
- 7 WIRE IN SIDEWALL.
- 6 WIRE ROUTED THROUGH FLOOR AT THIS POINT.
- 5 SEE LOAD CENTER/ATS ASM FOR ADDITIONAL INFORMATION.
4. SEE WIRING DIAGRAM-BODY,110V FOR ADDITIONAL INFORMATION.
3. ALL GROUND WIRE TO BE COVERED WITH TUBING 008041-02-000.
2. ALL 110V WIRE TO BE CLAMPED WITH CLAMP 010497-05-000 WITHIN 200MM OF OUTLET BOXES, USE SCREW 000G67-10-12B.
1. ALL WIRES TO BE SECURED WITH CLAMP 010495-01-000 OR CLIP 080734-01-000 EVERY 600MM. USE SCREW 000G67-10-12B UNLESS OTHERWISE SPECIFIED.



NOTES:

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000


FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

- 12D ELECTRICAL SYSTEM 30 AMP
- 299 ENTERTAINMENT CENTER EXT.W/O
- 14W DINETTE
- 78J ELECTRICAL SYSTEM-50 AMP
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY,110V		
SHEET 3	PART NO. 171651	REV



- NOTES:
1. WIRE MUST BE ROUTED THROUGH CLAMPS AS SHOWN.
 2. RUN 12V WIRE ALONG WITH REAR SLIDEOUT WIRE.
- 5 WITHOUT 49M
- 4 SEE LOAD CENTER/ATS ASM FOR ADDITIONAL INFORMATION.
- 3 MAKE LOOP AS SMALL AS POSSIBLE WHEN SLIDEOUT IS COMPLETELY RETRACTED.




X-X

FOR ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000


FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

12D	ELECTRICAL SYSTEM 30 AMP		
49M	SLEEP NUMBER BED-QUEEN SIZE		
78J	ELECTRICAL SYSTEM-50 AMP		
265	CODES/STANDARDS-CSA/CMVSS		
1B1	CODES/STANDARDS USA		
1B1	265	78J	12D
FIRST USED			
10 J32H			
DO NOT SCALE DRAWING			
TITLE: WIRING INSTL-BODY,110V			
SHEET 4	PART NO	171651	REV



VIEW EA

VIEW EC



DETAIL EB

- 2 WB FROM WIRE ASM-COACH TO PUR WIRE FROM INVERTER.
- 1 SEE WIRING INSTL-BODY, 12V FOR ADDITIONAL INFORMATION.



NOTES:

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

- 12D ELECTRICAL SYSTEM 30 AMP
- 40D INVERTER-DC/AC, 600 WATT
- 78J ELECTRICAL SYSTEM-50 AMP
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY, 110V		
SHEET 5	PART NO. 171651	REV



DETAIL FA

X-X

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

- 12D ELECTRICAL SYSTEM 30 AMP
- 78J ELECTRICAL SYSTEM-50 AMP
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265 78J 12D

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY,110V		
SHEET 6	PART NO 171651	REV

KEY	PART NUMBER	U/M	DESCRIPTION
	170909-01-700	EA	REMOTE - SERVICE PACK

170909-01-000
VENDOR NO.
PSVCJE1909

8				7				6				5		↓		4				3		2		1																																																	
		J32H		J37F				J35Z				J38N		J35P																																																											
BLK	14-UL	136131-06-040	1	136131-06-085	1	136131-06-030	136131-06-075	1	136131-06-040	1																																																															
	14-CA	136134-06-040	1	136134-06-085	1	136134-06-030	136134-06-075	1	136134-06-040	1																																																															
BLU	14-UL	136131-02-105		136131-02-270	1	136131-02-075	136131-02-165		136131-02-135	1																																																															
	14-CA	136134-02-105		136134-02-250	1	136134-02-075	136134-02-165		136134-02-135	1																																																															
BRN	14-UL	136131-03-040	1	136131-03-085	1	136131-03-120	136131-03-015		136131-03-040	1																																																															
	14-CA	136134-03-040	1	136134-03-085	1	136134-03-120	136134-03-015		136134-03-040	1																																																															
GLD	12-UL	N/A		136135-10-085		N/A	136135-10-065		136135-10-046		21M	54E																																																													
	12-CA	N/A		136136-10-085		N/A	136136-10-065		136136-10-046		21M	54E																																																													
GRN	12-UL	136135-08-090		136135-08-065		136135-08-110	136135-08-095		136135-08-095		78J																																																														
	12-CA	136136-08-090		136136-08-065		136136-08-110	136136-08-095		136136-08-095		78J																																																														
	12-UL	136135-08-070		136135-08-048		136135-08-093	136135-08-060		136135-08-075		12D																																																														
	12-CA	136136-08-070		136136-08-048		136136-08-093	136136-08-060		136136-08-075		12D																																																														
GRN 2	12-UL	136135-14-054		136135-14-080		136135-14-054	136135-14-054		136135-14-054		12D																																																														
	12-CA	136136-14-054		136136-14-080		136136-14-054	136136-14-054		136136-14-054		12D																																																														
PUR	14-UL	136131-04-090	1	136131-04-065	1	136131-04-140	136131-04-160	1	136131-04-090	1																																																															
	14-CA	136134-04-090	1	136134-04-065	1	136134-04-140	136134-04-160	1	136134-04-090	1																																																															
RED	12-UL	136135-07-090		136135-07-065		136135-07-110	136135-07-095		136135-07-095																																																																
	12-CA	136136-07-090		136136-07-065		136136-07-110	136136-07-095		136136-07-095																																																																
WHT	12-UL	136135-09-025		136135-09-051		136135-09-075	136135-09-040		136135-09-025		1B2																																																														
	12-CA	136136-09-025		136136-09-051		136136-09-075	136136-09-040		136136-09-025		1B2																																																														
YEL	14-UL	136131-05-020		136131-05-065		136131-05-030	136131-05-052		136131-05-020																																																																
	14-CA	136134-05-020		136134-05-065		136134-05-030	136134-05-052		136134-05-020																																																																
YEL 2	14-UL	136131-13-040	1	136131-13-085	1	136131-13-041	136131-13-055		136131-13-040	1																																																															
	14-CA	136134-13-040	1	136134-13-085	1	136134-13-041	136134-13-055		136134-13-040	1																																																															
GRY	14-UL	N/A		N/A		N/A	136131-15-075	1	-----		14C																																																														
	14-CA	N/A		N/A		N/A	136134-15-075	1	-----		14C																																																														
MAIN	10-UL	136137-01-070		136137-01-048		136137-01-093	136137-01-060		136137-01-075		12D																																																														
	10-CA	136138-01-070		136138-01-048		136138-01-093	136138-01-060		136138-01-075		12D																																																														
	6-3 UL	136139-01-070		136139-01-048		136139-01-093	136139-01-060		136139-01-075		78J																																																														
	6-3 CA	136140-01-070		136140-01-048		136140-01-093	136140-01-060		136140-01-075		78J																																																														
MAIN GROUND		N/A	2	N/A	2	136145-01-030	136145-01-045		-----																																																																
ATS GROUND		136145-01-020		136145-01-020		136145-01-067	136145-01-061		136145-01-020																																																																
CONDUIT ASM-CENTRAL A/C		151704-01-015		151704-01-015		151704-01-015	151704-01-015		151704-01-015																																																																
NOTES:														FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000										FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000										DO NOT SCALE DRAWING										TITLE: LOAD CENTER/ATS ASM										SHEET 1 OF 5 PART NO. 171004 REV										REF: 1 10/15/2009									
8				7				6				5		↑		4				3		2		1																																																	

8

7

6

5

4

3

2

1

THROW IN WIRE #1

136131-03-145

1

136131-03-105

1

136131-03-080

3

136131-03-075

4

136131-03-020

1

THROW IN WIRE #2

136131-06-028

1

136131-12-040

21W

136131-04-025

1

10X

OR

10G

136131-03-017

4

THROW IN WIRE #3

136131-12-057

1

136131-12-070

1

136131-12-052

1

10X

OR

10G

136131-12-057

1

THROW IN WIRE #4

136131-13-023

1

136131-13-028

1

136131-12-250

2

136131-12-030

1

136131-13-028

1

THROW IN WIRE #5

136131-12-140

6

136131-12-150

6

136131-12-006

1

40D

136131-15-010

1

14C

136131-12-145

6

THROW IN WIRE #6

136131-12-006

1

40D

136131-12-006

1

40D

136131-04-006

1

136131-12-006

1

136131-12-006

1

40D

THROW IN WIRE #7

136131-04-018

1

49M

136131-04-006

1

136131-12-035

1

45X

136131-12-260

6

136131-04-018

1

49N

THROW IN WIRE #8

136135-10-040

136131-04-070

1

45X

136131-04-018

49N

136135-10-040

THROW IN FRONT TV

136135-10-040

136131-12-008

136134-12-008

SLIDEOUT WIRE #1

136151-03-017

5

136151-03-017

5

136151-03-028

3

136151-03-028

2

136151-03-017

5

SLIDEOUT WIRE #2

136151-06-017

5

136151-06-017

5

136151-04-017

2

136151-06-028

2

136151-06-017

5

SLIDEOUT WIRE #3

136151-12-017

5

136151-12-017

5

136151-04-023

2

136151-12-028

2

136151-12-017

5

SLIDEOUT WIRE #4

136151-13-017

5

136151-13-017

5

136151-12-023

2

136151-15-028

2

14C

136151-13-017

5

SLIDEOUT WIRE #5

136151-04-018

2

136152-10-019

7

136151-04-017

2

136152-10-019

7

SLIDEOUT WIRE #6

136151-04-015

2

136151-03-026

4

136151-04-018

2

SLIDEOUT WIRE #7

136151-02-023

2

136151-02-023

2

7

SEE DETAIL EG.

6

SEE DETAIL EF.

5

SEE DETAIL EE.

4

SEE DETAIL ED.

3

SEE DETAIL EC.

2

SEE DETAIL EB.

1

SEE DETAIL EA.

NOTES:

171004

DWG NO

TRANSFORMER (REF)

DETAIL BA

(LOAD CENTER SHOWN FROM THE BACK SIDE)

21W

DINING,BUFFET,TV

78J

ELECTRICAL SYSTEM-50 AMP

49N

SLEEP NUMBER BED-KING SIZE

49M

SLEEP NUMBER BED-QUEEN SIZE

45X

BED - BUNKS

40D

INVERTER-DC/AC,600 WATT

12D

ELECTRICAL SYSTEM 30 AMP

14C

FIREPLACE-ELECTRIC

10X

SOFA (BEDROOM)

10G

SOFA (BEDROOM) ULTRALEATHER

265

CODES/STANDARDS-CSA/CMVSS

1B1

CODES/STANDARDS USA

1B1

265

12D

78J

FIRST USED

10 J-SERIES

DO NOT SCALE DRAWING

TITLE:

LOAD CENTER/ATS ASM

SHEET 2

PART NO

171004

REV

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000



X-X

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

10/15/2009



NOTES:

1. ALL GROUND WIRES TO BE COVERED WITH TUBING 8041-02-000.
2. GROUND WIRES ARE NOT SHOWN FOR CLARITY.
3. ALL WIRES TO BE CLAMPED WITHIN 200MM OF ATS.
4. ALL 110V STRANDED WIRE W/O TERMINALS TO BE STRIPPED 10MM AND SOLDER DIPPED.
5. ATTACH WIRES TO BACKSIDE OF LOAD CENTER, USE EXISTING HOLES AND TIE-WIRE 116673-01-000.
6. REMOVE 400MM FROM OUTER JACKET ON ALL WIRES ENTERING LOAD CENTER AND TRIM INDIVIDUAL CONDUCTORS AS REQUIRED TO MAKE INTERNAL CONNECTIONS.

INSTALL LABEL ON FRONT COVER PLATE BELOW THE BREAKERS

LOOSEN LEFT BUSS BAR MOUNTING SCREW, INSERT BRACKET-BREAKER HOLD DOWN UNDER SCREW, ORIENTATE BRACKET TOWARD MAIN BREAKER AS SHOWN AND TIGHTEN SCREW.

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

10 J-SERIES

DO NOT SCALE DRAWING

TITLE: LOAD CENTER/ATS ASM

SHEET 4

PART NO 171004


REV

D


C

B


A




DETAIL EE




DETAIL EF




DETAIL ED




DETAIL EC



DETAIL EG



DETAIL EA



DETAIL EB

2 THE BLACK INDIVIDUAL CONDUCTORS FOR EACH SPECIFIC COLORED CIRCUIT ARE TO BE CONNECTED TOGETHER.
THE WHITE INDIVIDUAL CONDUCTORS FOR EACH SPECIFIC COLORED CIRCUIT ARE TO BE CONNECTED TOGETHER.
ALL GROUND WIRES ARE TO BE CONNECTED TOGETHER.

1 APPLY 300MM OF CONDUIT-CONVOLUTE 41953-05-000 OVER WIRE AT DIMENSION SHOWN AND SECURE BOTH ENDS OF TUBING TO WIRE WITH TAPE 8363-01-000.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

78J ELECTRICAL SYSTEM-50 AMP
12D ELECTRICAL SYSTEM 30 AMP
265 CODES/STANDARDS-CSA/CMVSS
1B1 CODES/STANDARDS USA

1B1 265 12D 78J

FIRST USED

10 J-SERIES

DO NOT SCALE DRAWING

TITLE: LOAD CENTER/ATS ASM

SHEET 5 PART NO 171004 REV

8

7

6

5

4

3

2

1

RELEASE

REV DATE

DWG NO


171650

REV ZONE

REVISION RECORD

DATE

DFT-ORIG



PANEL-SERVICE
132862-07-02B
SCREW
000G67-10-10B (4)

PLATE-WALL, TELEPHONE/COAX
149557-03-01A
SCREW
000G39-08-08B (2)

COAX GLD

COAX RED

VIEW AA

WIRE ASM-COACH
170421-01-000

CHANNEL-WIRE PATH, TOP
162012-03-02B (4)
SCREW
000G39-08-08B (8)

WIRE ASM-CHASSIS
TO SLIDEOUT RAM
SEE SHEET 8

2 PIN HOUSING
TO WIRE ASM-
COMPARTMENT LAMPS
(IN FLOOR)

PANEL-RECEPTACLE
151376-02-02B
ADAPTER
082134-01-000
NUT
082136-01-000
LABEL
157486-01-02A
SCREW
000G67-10-12B (4)

YEL-COAX
TO PANEL-RECEPTACLE

HOUSINGS
TO AWNING
CONTROL BOX

300 DROP
CABLE ASM-MODULAR
FROM MONITOR PANEL
TO INVERTER

8 PIN HOUSINGS (6)
DETAIL EA

4 PIN HOUSING
TO WATER HEATER
WIRE ASM-JUMPER, WATER HTR
142263-01-000

2 PIN HSG
TO WATER PUMP

2 PIN HOUSING
TO WIRE ASM-WATER TANK

WIRE ASM-WATER TANK
151317-01-000

2 PIN HOUSING
TO SLIDEOUT RAM MOTOR
(SEE SHEET 8)

WIRE ASM-THERMOSTAT
FROM WIRE ASM-COACH
TO CENTRAL A/C

WIRE ASM-THERMOSTAT
135131-02-000

4 PIN HOUSING
TO FURNACE

4
NW, WE
TO COMPARTMENT LAMP
TELEPHONE WIRE
TO PLATE-WALL, PHONE
COAX (RED)
COAX (GLD)
TO PLATE-WALL, PHONE

2 PIN HOUSING TO
WIRE ASM-AUX
HOLDING TANK
151316-02-000

8 PIN HOUSING (3)
DETAIL EB

2 PIN HOUSING
TO WIRE ASM-
COMPARTMENT LAMPS

WC, WE
TO COMPARTMENT LAMP

2 PIN HOUSING TO
WIRE ASM-MAIN HOLDING
151317-02-000

5 WIRE PASSES THROUGH FLOOR AT THIS POINT.

4 CONNECT TELEPHONE WIRE TO MATCHING
COLORS ON PLATE-WALL, TELEPHONE.

3. ROUTE TANK SENSOR WIRES SO THEY DO NOT PASS OVER
SENSORS. USE WIRE TIE MOUNT 155366-01-000 AND WIRE
TIE 8343-01-000 AS NEEDED. TANK SURFACE MUST BE CLEANED
USING ISOPROPYL ALCOHOL AND PRIME WITH PRIMER 94.

2. SEE WIRING DIAGRAM-BODY, 12V FOR ADDITIONAL INFORMATION.

1. ALL WIRES TO BE CLAMPED WITH CLAMP 010495-01-000
OR WIRE TIE 008343-02-000 EVERY 600MM UNLESS OTHERWISE
SPECIFIED.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

WINNEBAGO
INDUSTRIES

COPYRIGHT 2010
WINNEBAGO
INDUSTRIES, INC.

DFT-OR	ORIG. DATE
CHK-OR	
P.E.	ALL DIMENSIONS ARE IN MILLIMETERS
M.E.	FIRST USED
DSNR	10 J32H
UNSPECIFIED TOLERANCES ARE:	MATERIAL:
WHOLE DIM (X) ± 3	
ONE-PLACE (X.X) ± 1.5	
TWO-PLACE (X.XX) ± 0.50	
ANGLE ± 1°	
THIRD ANGLE PROJECTION	

DO NOT SCALE DRAWING

TITLE:
WIRING INSTL-BODY, 12V

SHEET 1 OF 8




PART NO 171650

REV

REF:

1

3/4/2010



- 7 ADD CONDUIT 041953-07 TO COVER EXPOSED WIRES.
- 6 MOUNT DEVICE AS CLOSE TO WIRE DROP FROM CABINET AS POSSIBLE.
- 5 WIRE IN ROOF.
- 4 WIRE IN SIDEWALL.
- 3 WIRE PASSES THROUGH FLOOR AT THIS POINT.
2. SEE WIRING DIAGRAM-BODY, 12V FOR ADDITIONAL INFORMATION.
1. ALL WIRES TO BE CLAMPED WITH CLAMP 010495-01-000 OR WIRE TIE 008343-02-000 EVERY 600MM UNLESS OTHERWISE SPECIFIED.


- 12 PLACE CONNECTOR HERE TO MAKE CONNECTION TO WIRE ASM. USE CONNECTOR 058028-01-000 (2).
- 11 SEE WIRING INSTL-BODY, 12V FOR ADDITIONAL INFORMATION.
- 10 CONNECTS TO FRONT OF SATELLITE PREP PLATE.
- 9 CONNECTS TO REAR OF SATELLITE PREP PLATE.
- 8 INSTALL GASKET ON BACKSIDE OF ONE PLACE AFTER INSTALLATION OF THERMOSTAT, MAKING SURE THAT THE GASKET COVERS AND SEALS THE HOLE THAT THE WIRES PASS THROUGH.

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 1JM HOME THEATER SOUND SYSTEM
- 42Z LOUNGE SEATING-THEATER STYLE
- 42H REST EASY-DUAL CONTROL
- 41L REST EASY DUAL CTL ULTRALE LH
- 41H REST EASY, ULTRALEATHER
- 41F REST EASY MULTI POS LOUNGE
- 22F DINETTE, U-SHAPED ULTRALEATH
- 22B DINETTE - U-SHAPED
- 40D INVERTER-DC/AC, 600 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY, 12V		
SHEET 2	PART NO 171650	REV



- 8 UPON FIRST POWER-UP, THE DISPLAY PANEL WILL PROMPT FOR "GEN TYPE". USE THE ARROW KEYS AND SCROLL TO "GAS/LP" AND PRESS ENTER. NEXT, IT WILL PROMPT FOR "SAFE TYPE". USE THE ARROW KEYS TO SCROLL TO "IGNITION" AND PRESS ENTER. SEE OWNER'S MANUAL FOR ADDITION INFORMATION.
- 7 CONNECTS INLINE OF THE YELLOW VIDEO CABLE. WRAP BOTH ENDS OF FILTER CONNECTIONS WITH TAPE 8363-01-000 TO SECURE FILTER.
- 6 INSTALL GASKET ON BACKSIDE OF ONE PLACE AFTER INSTALLATION OF THERMOSTAT, MAKING SURE THAT THE GASKET COVERS AND SEALS THE HOLE THAT THE WIRES PASS THROUGH.
- 5 WIRE IN ROOF.
- 4 TOP OF LAMP SHADE/GLOBE TO BE NO LESS THEN 150MM BELOW BOTTOM OF CABINET.
- 3 WIRE PASSES THROUGH FLOOR AT THIS POINT.
2. SEE WIRING DIAGRAM-BODY,12V FOR ADDITIONAL INFORMATION.
1. ALL WIRES TO BE CLAMPED WITH CLAMP 010495-01-000 OR WIRE TIE 008343-02-000 EVERY 600MM UNLESS OTHERWISE SPECIFIED.


NOTES:

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 32W GENERATOR-START,AUTO SYSTEM
- 1JF HOME THEATER SYS-WITHOUT
- 29Q SOLAR PANEL-10 WATT
- 25D STEREO SYSTEM/W/CD/DVD REAR
- 14W DINETTE
- 13T SOFA/BED RH
- 41N SOFA/BED ULTRALEATHER
- 571 RADIO SPEAKERS
- 1JM HOME THEATER SOUND SYSTEM
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA
- 1B1 265

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY,12V		
SHEET 3	PART NO. 171650	REV



- NOTES:
- 4 WRAP BOTH ENDS WITH TAPE 8363-01-000 TO SECURE CONNECTION.
 - 3 FOR POSITIONING DIMENSIONS SEE WIRING INSTL-BODY, 110V.
 - 2 MOUNT SWITCH AND SPACER TO BLOCK ON JAMB ADJUST HEIGHT TO MATCH MAGNET.
 - 1 MOUNT MAGNET USING PILOT HOLES IN SCREEN DOOR FRAME. MOUNT WITH MAGNET TOWARD SWITCH.

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

X-X

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 27A EXT FULL BODY PAINT PKG #1
- 27G EXTERIOR GRAPHICS PACKAGE #1
- 92K EXTERIOR GRAPHICS PACKAGE #2
- 92A EXT FULL BODY PAINT PKG # 2
- 24B EXT FULL BODY PAINT PKG #4
- 24C EXT FULL BODY PAINT PKG # 3
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY, 12V		
SHEET 4	PART NO. 171650	REV

52N
2

SWITCH-AWNING
108357-07-000
ACTUATOR
108356-12-01A
FFR,FFP,FFN
SWITCH-BLANK
096241-03-000

SWITCH-COMPT LIGHTS
108357-01-000
ACTUATOR-SWITCH
108356-14-01A
CIRCUITS WC,WA

PLATE-SWITCH
158431-03-04B
SCREW
000G11-06-10B (6)

SWITCH-STEP
108357-19-000
CIRCUITS ER,ES

SWITCH-COACH BATT
108357-17-000
ACTUATOR-SWITCH
108356-19-01A
CIRCUITS KF,LG,
LJ,LJ,LH,KF,KF,LK

DETAIL EA 3


SWITCH-CHASSIS BATT
108357-17-000
ACTUATOR-SWITCH
108356-20-01A
CIRCUITS UUC,TTY,UUB,
UUB,TTZ,UUC,UUC,UUA

SWITCH-PUMP
108357-15-000
ACTUATOR
108356-03-01A
JY,AG,JA,AF,JS

SWITCH-SERVICE LAMP
108357-01-000
ACTUATOR
108356-01-01A
WC,WA


SWITCH-AUTO LEVEL
108357-18-000
ACTUATOR-SWITCH
108356-03-01A
SSD,SSE,SSC,SSF,SSE

DETAIL EB 3




DETAIL EC

SWITCH-ROCKER
135740-01-01A
135740-02-01A (2)
SWITCH-BASE
135741-03-01A
SWITCH-BEZEL
135742-25-02A
SCREW
000G11-08-08B (4)




DETAIL EG

SWITCH-ROCKER
135740-01-01A (2)
SWITCH-BASE
135741-02-01A
SWITCH-BEZEL
135742-19-02A
SCREW
000G11-08-08B (4)



DETAIL EN

SWITCH-ROCKER
135740-01-01A
135740-03-01A
SWITCH-BASE
135741-02-01A
SWITCH-BEZEL
135742-17-02A
SCREW
000G11-08-08B (4)



DETAIL EP 41M

SWITCH-ROCKER
135740-01-01A
SWITCH-BASE
135741-01-01A
SWITCH-BEZEL
135742-12-02A
SCREW
000G11-06-16B (2)

41M VENT-POWER VENTILATOR


52N AWNING - PATIO, ELECTRIC

265 CODES/STANDARDS-CSA/CMVSS


1B1 CODES/STANDARDS USA

1B1 265

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY, 12V		
SHEET 5	PART NO 171650	REV




DETAIL ED





DETAIL EE

SWITCH-ROCKER
135740-06-01A
SWITCH-BASE
135741-01-01A
SWITCH-BEZEL
135742-35-02A
SCREW
000G11-08-08B (2)




DETAIL EK



DETAIL EH

SWITCH-PUMP
108357-15-000
ACTUATOR
108356-23-01A
PLATE
098351-07-03A
SCREW
000G11-06-10B (2)



LABEL-SLIDEOUT,DRIVERS,FRT
163992-01-01A



SLIDEOUT-ELEC,FRONT
171341-01-000(2)
SCREW
076790-05-000 (4)

CONNECT TO 12-PIN
HOUSING WITH CIRCUITS
WJ,GGE,GGF,GGD,
DR,DU,WP,WN.

CONNECT TO 12-PIN
HOUSING WITH CIRCUITS
WWE,MMB,MMD,MMA,MMC,
LLZ,WWG,WWF.



SEE DETAIL ED

PLATE-SWITCH
144363-09-02B
SWITCH
108357-06-000
ACTUATOR
108356-01-01A
NUT
000D65-08-00B (2)
LABEL
116220-02-000
CONNECTS TO
CIRCUITS PPM
,PPN,PPS,PPT.




PLATE-KEY, SLIDE ROOM
163987-01-02B
SCREW
076790-05-000 (4)


LABEL-SLIDEROOM CONTROL, MAN
163988-02-01A

SWITCH-KEY,SPST-ILLINOIS LCK
163097-01-000
(CONNECTS TO CIRCUITS DY & DDJ)

WARNING CRUSH HAZARD. Keep people and objects clear of the inside and the outside of the slideout room when operating. Failure to comply could result in death or serious injury.


LABEL-WARNING, SLIDEOUT
116549-01-000

DETAIL EJ




DETAIL EL

SWITCH-ROCKER
135740-02-01A
SWITCH-BASE
135741-01-01A
SWITCH-BEZEL
135742-07-02A
SCREW
000G11-08-08B (2)



DETAIL EM

SWITCH-ROCKER
135740-01-01A
SWITCH-BASE
135741-01-01A
SWITCH-BEZEL
135742-07-02A
SCREW
000G11-08-08B (2)



DETAIL ER

SWITCH-ROCKER
135740-01-01A
SWITCH-BASE
135741-01-01A
SWITCH-BEZEL
135742-30-02A
SCREW
000G11-08-08B (2)

4 WITHOUT 1B2 OR 53D

3 FOR SWITCH ORIENTATION SEE DETAIL EK.


2 WITHOUT 52N

1. SWITCHES ARE TO BE INSTALLED AS SHOWN ON THIS DRAWING.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

X-X
FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000



SATELLITE
ELEVATION
SENSOR
DETAIL GD

1JM {
SPEAKER-ROUND,CEILING
160867-01-01A (2)
SCREW
OG1208-12-170 (8)

LIGHT-OVAL,SGL,W/SW,FROSTED
170693-01-01A (7)(UP TO 09-27-09)
LIGHT-OVAL,SGL,W/SW,OPTIC
170693-02-02A (7)(AFTER 09-28-09)
WASHER-PLASTIC
087277 03 000 (5)
SCREW
000G11-08-08B (10)

LIGHT-DOME,DBL,W/O SW,FROSTD
170693-06-01A (UP TO 09-27-09)
LIGHT-DOME,DBL,W/O SW,OPTIC
170693-07-02A (AFTER 09-28-09)

LIGHT-DOME,SHOWER GLASS
164040-01-01A

LIGHT-HALOGEN
146048-01-000
SCREW
SUPPLIED WITH LIGHT

LIGHT-HALOGEN,ROUND
165643-01-01A (13)

2 LAMP LOCATED IN SERVICE COMPARTMENT.
1 LAMP LOCATED IN POWER CORD COMPARTMENT.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000


X-X

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

1JM HOME THEATER SOUND SYSTEM
265 CODES/STANDARDS-CSA/CMVSS
1B1 CODES/STANDARDS USA

1B1 265

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE:		
WIRING INSTL-BODY,12V		
SHEET 6	PART NO	REV
	171650	



- NOTES:
- 4 SENSOR SUPPLIED WITH SATELLITE ASSEMBLY.
 - 3 WRAP BRACKET LEGS AROUND ANTENNA BASE.
 - 2 REMOVE ALL SHIPPING RESTRAINTS AND FIRMLY INSERT THE SUPPLIED PLUGS INTO THE APPROPRIATE SIZED HOLES AS SPECIFIED IN THE INSTALLATION PROCESS.
 - 1 SEE ANTENNA INSTALLATION MANUAL FOR CORRECT INSTALLATION PROCEDURE.

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 48R SAT TV SYSTEM IN-MOTION
- 41M VENT-POWER VENTILATOR
- 25D STEREO SYSTEM/W/CD/DVD REAR
- 78K SATELLITE DISH-AUTOMATIC
- 48Q SATELLITE DISH & ELEV.SENSOR
- 29Q SOLAR PANEL-10 WATT
- 1D5 ENTERTAINMENT CENTR/EXT W/CD
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY, 12V		
SHEET 7	PART NO 171650	REV

FROM WIRE ASM-COACH
10 PIN HSG
CIRCUITS
WWH,MMB,MMD,MMA,
MMC,LLZ,WWG,WWF.

FROM WIRE ASM-SLIDEOUT POWER
4 PIN HSG
CIRCUITS
LLP,LLR

FROM WIRE ASM-SLIDEOUT POWER
4 PIN HSG
CIRCUITS
LLK,LLL,LLN,LLM

FROM WIRE ASM-COACH
10 PIN HSG
CIRCUITS
VVR,GGE,GGF,GGD,
DR,DU,VVP,VVN.

FROM WIRE ASM-CHASSIS
6 PIN HSG
CIRCUITS
GGH,GGG,GGJ
GGL,GGK,GGM

RIGHT REAR SLIDEOUT MODULE
CONTROL SINGLE HIGH SPEED

FROM WIRE ASM-SLIDEOUT RAM
5 PIN HSG
CIRCUITS
LLV,LLX

FRONT LEFT SLIDEOUT MODULE
CONTROL-DIGISYNC,HIGH SPEED

WIRE ASM-SLIDEOUT RAM
5 PIN HSG
CIRCUITS
LLS,LLT,LLW,LLU

SECTION HA-HA

WIRE ASM-SLIDEOUT
RAM,REAR

WIRE ASM-SLIDEOUT RAM,REAR
171477-01-063

REAR BDRM RAM
2 PIN HSG
TO SLIDEOUT RAM MOTOR
FROM WIRE ASM-SLIDEOUT RAM
CIRCUITS LLV,LLX

WIRE ASM-CHASSIS

FRONT LEFT REAR RAM
2 PIN HSG
TO SLIDEOUT RAM MOTOR
FROM WIRE ASM-SLIDEOUT RAM
CIRCUITS LLU,LLW
3 PIN HSG
TO SLIDEOUT RAM ENCODER
FROM WIRE ASM-CHASSIS
CIRCUITS G GK,GGM,GGL

FRONT LEFT FRONT RAM
2 PIN HSG
TO SLIDEOUT RAM MOTOR
FROM WIRE ASM-SLIDEOUT RAM
CIRCUITS LLS,LLT
3 PIN HSG
TO SLIDEOUT RAM ENCODER
FROM WIRE ASM-CHASSIS
CIRCUITS GGG,GGJ,GGH

- 4 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL INFORMATION.
- 3 SEE CHASSIS ELECTRICAL BOX ASM FOR ADDITIONAL INFORMATION.
2. SEE WIRING DIAGRAM-BODY,12V FOR ADDITIONAL INFORMATION.
1. ALL WIRES TO BE CLAMPED WITH CLAMP 010495-01-000
OR WIRE TIE 008343-02-000 EVERY 600MM, UNLESS OTHERWISE
SPECIFIED.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000


FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265

FIRST USED		
10 J32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-BODY,12V		
SHEET 8	PART NO 171650	REV



KEY PART NUMBER

2	076319-01-700	EA	HEAD-ANTENNA, AMPLIFIED
3	076319-01-701	EA	GEAR-ELEVATING, PLASTIC
4	076319-01-702	EA	SHAFT ASM-ELEVATING
5	076319-01-711	EA	BASE & LIFT ASM
7	076319-01-705	EA	GROMMET-NYLON, 7/8"ID
8	076319-01-708	EA	DECAL-CRANK
9	076319-01-707	EA	SPRING-HANDLE
11	076319-01-712	EA	PLATE - CEILING
12	076319-01-715	EA	NUT (GEAR HOUSING)
14	076319-01-713	EA	PLATE-BASE, STEEL
15	076319-01-703	EA	BEARING-NYLON, 5"OD
16	076319-01-714	EA	HOUSING, ROTATING GEAR
17	076319-01-704	EA	BEARING-NYLON, 1.25"OD
18	076319-01-709	EA	HANDLE-HEAD DIRECTIONAL
	076319-01-716	EA	TUBING, ELEVATING

076319-23-000
VENDOR NO.

RVSA U/V
2200046
RP-4000
2762802
3200658
5413002
2160822
3200608
2200047
3100523
3200656
2200049
3200657
200644
RP-2900


CONTACT WINNEBAGO PART SALES FOR UNLISTED COMPONENT(S)

VENDOR NO.

KEY	PART NUMBER	U/M	DESCRIPTION
	087694-01-700	EA	BULB

087694-01-000
VENDOR NO.
GE561

KEY	PART NUMBER	U/M	DESCRIPTION	108354-01-01A	VENDOR NO.
	108354-01-700	EA	BULB-COURTESY LIGHT		395-B




134940-06-01A

KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
1	134940-01-702	EA	CHASSIS - SILKSCREENED	CC0558-00
2	134940-01-701	EA	SWITCH-SPST/ON-OFF/BLK W/LGT	L0109
3	096983-01-701	EA	SWITCH - SPST/MOM 2 TERMINAL	L0111-00
4	096983-01-702	EA	SWITCH - MOM/OFF/MOM/3 TERM	L0112-00
5	096983-01-703	EA	SWITCH - ON/ON	L0115-00
10	100258-10-701	EA	GAUGE-HR METER ONLY (LCD)	L0775-00
11	134940-06-700	EA	PC BOARD - SENSOR SYSTEM/RED	L5131-02
CONTACT WINNEBAGO PART SALES FOR UNLISTED COMPONENT(S)				

134940-07-01A

KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
1	134940-01-702	EA	CHASSIS - SILKSCREENED	CC0558-00
2	134940-01-701	EA	SWITCH-SPST/ON-OFF/BLK W/LGT	L0109
3	096983-01-701	EA	SWITCH - SPST/MOM 2 TERMINAL	L0111-00
4	096983-01-703	EA	SWITCH - ON/ON	L0115-00
5	134940-02-700	EA	SWITCH - DUMMY	L0118
11	134940-06-700	EA	PC BOARD - SENSOR SYSTEM/RED	L5131-02
CONTACT WINNEBAGO PART SALES FOR UNLISTED COMPONENT(S)				


134940-08-01A				
KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
1	134940-04-700	EA	CHASSIS - SILKSCREENED	CE0136-00
2	134940-01-701	EA	SWITCH-SPST/ON-OFF/BLK W/LGT	L0109
3	096983-01-701	EA	SWITCH - SPST/MOM 2 TERMINAL	L0111-00
4	096983-01-702	EA	SWITCH - MOM/OFF/MOM/3 TERM	L0112-00
5	096983-01-703	EA	SWITCH - ON/ON	L0115-00
10	100258-10-701	EA	GAUGE-HR METER ONLY (LCD)	L0775-00
11	134940-06-700	EA	PC BOARD - SENSOR SYSTEM/RED	L5131-02
12	134940-04-701	EA	BOARD - PC - SOLAR LIGHT	L5121-01
CONTACT WINNEBAGO PART SALES FOR UNLISTED COMPONENT(S)				



134940-10-01A				
KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
1	134940-10-700	EA	SILKSCREENED CHASSIS	CE0129-00
2	096983-01-703	EA	SWITCH - ON/ON	L0115-00
3	134940-01-701	EA	SWITCH-SPST/ON-OFF/BLK W/LGT	L0109
4	096983-01-701	EA	SWITCH - SPST/MOM 2 TERMINAL	L0111-00
9	134940-06-700	EA	PC BOARD - SENSOR SYSTEM/RED	L5131-02
CONTACT WINNEBAGO PART SALES FOR UNLISTED COMPONENT(S)				

137135-05-000			
KEY	PART NUMBER	U/M DESCRIPTION	VENDOR NO.
	120233-01-714	EA CLIP-E	5160818
	120233-01-737	EA PLATE/INT-W/DIRECTIONAL HDLE	RK-CEIL
	120233-01-738	EA HDW PKG-HANDLE/SPRING/WASHER	RK-HAND
	120233-04-703	EA KIT-DIRECTIONAL HDL UPGRADE	RP-RM46
	137135-01-703	EA KIT ELEV-SHAFT/PLUG/SPRING	RP-4400
	137135-01-704	EA PIN - 1/4" X 3.25"	2160813
	137135-01-708	EA TURRET	3100728
	137135-01-710	EA PLATE - ROTATE LIMIT	3720052
	137135-01-712	EA BEARING - OUTER	2590347
	137135-01-713	EA TURRET BASE	3100730
	137135-01-714	EA GEAR - ELEVATING SHAFT	2200465
	137135-01-715	EA BEARING - INNER	2590348
	137135-01-717	EA BOLT - FLAT HEAD	2160362
	137135-01-719	EA BRACKET - PIVOT	2744945
	137135-01-722	EA CLAMP	2590343

J32H
144818-08



- 4 PUT IN INFO CASE.
- 3 SUPPLIED WITH RADIO
- 2 BEND TABS ON MOUNTING BRACKET SUPPLIED WITH RADIO, TO HOLD IN PLACE.
1. SEE WIRING INSTL-BODY FOR ADDITIONAL INFORMATION.


NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000


FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

1D5 ENTERTAINMENT CENTER/EXT W/CD


FIRST USED		
04 MOTORHOMES		
DO NOT SCALE DRAWING		
TITLE: ENTERTAINMENT CENTER COMPL		
SHEET 3	PART NO 144818	REV




DETAIL EB



DETAIL ED



DETAIL EA



DETAIL EC

- 5 FULLY INSERT ANTENNA EXTENSION INTO PIGTAIL PROVIDED
ON RADIO & WRAP WITH TAPE 008363-01-000 (100mm).
- 4 COAX ON TABS -02, & -03 ONLY.
- 2 PLYWOOD ON TAB -02 ONLY.
- 1 SEE WIRING INSTL-BODY FOR ADDITIONAL INFORMATION.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

FIRST USED		
04 MOTORHOMES		
DO NOT SCALE DRAWING		
TITLE: ENTERTAINMENT CENTER COMPL		
SHEET 4	PART NO 144818	REV

KEY	PART NUMBER	U/M DESCRIPTION
	123775-01-700	EA BULB - 10 WATT - HALOGEN

146048-01-01A
VENDOR NO.
71-JC10

154474-04-01A			
KEY	PART NUMBER	U/M DESCRIPTION	VENDOR NO.
	154474-04-703	EA BOARD RF ASSEMBLY N/C	100087
	154474-04-705	EA CABLE OUT DUAL TOP PCBA N/C	20034-1
	154474-04-706	EA LNB DUAL EAGLE ASPEN N/C	1863-1

154474-04-02A			
KEY	PART NUMBER	U/M DESCRIPTION	VENDOR NO.
	154474-04-702	EA DOME ONLY-REPLACEMENT-BLACK	1850-B-LP-FS
	154474-04-703	EA BOARD RF ASSEMBLY N/C	100087
	154474-04-705	EA CABLE OUT DUAL TOP PCBA N/C	20034-1
	154474-04-706	EA LNB DUAL EAGLE ASPEN N/C	1863-1

KEY	PART NUMBER	U/M	DESCRIPTION	163097-01-000	VENDOR NO.
	163097-01-700	EA	KEY - #2382 (ILLINOIS LOCK)		2382
	163097-01-701	EA	KEY - #2341 (MILLER DIAL)		PART SALES


163598-01-01A			
KEY	PART NUMBER	U/M	DESCRIPTION
	154474-04-706	EA	LNB DUAL EAGLE ASPEN N/C
	163598-01-700	EA	BOARD CIRCUIT N/C
	163598-01-701	EA	STUFFED PCB,CWIM DVB N/C
VENDOR NO.			
			1863-1
			1990-RF-LP KIT
			438

163598-01-02A			
KEY	PART NUMBER	U/M	DESCRIPTION
	154474-04-702	EA	DOME ONLY-REPLACEMENT-BLACK
	154474-04-706	EA	LNB DUAL EAGLE ASPEN N/C
	163598-01-700	EA	BOARD CIRCUIT N/C
	163598-01-701	EA	STUFFED PCB,CWIM DVB N/C
VENDOR NO.			
			1850-B-LP-FS
			1863-1
			1990-RF-LP KIT
			438

KEY	PART NUMBER	U/M	DESCRIPTION
	165170-01-700	EA	LENS

165170-01-01A
VENDOR NO.
81230-LENS

KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
	169536-01-700	EA	REMOTE - SERVICE PACK	PSVCAWM970



173464-08
J32H
J35P
J37F

1. SEE WIRING INSTL-BODY FOR ADDITIONAL INFORMATION.

NOTES:



FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000



1D5 ENTERTAINMENT CENTER/EXT W/CD

10 MOTORHOMES

ENTERTAINMENT CENTER COMPL



173464-01
173464-03
173464-07
173464-08



1D5 ENTERTAINMENT CENTER/EXT W/CD

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000


X-X

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

10 MOTORHOMES

ENTERTAINMENT CENTER COMPL

D-Series
E-Series
J-Series
169848-05



- 6 MOUNT ANTENNA SUCH THAT BASE IS SQUARE W/REAR OF ROOF CAP & HOLE IS DIRECTLY OVER HOLE IN FIBERGLASS. SEAL HOLE IN ROOF CAP, BASE AT SCREWS.
- 5 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
- 4 USE HOLE IN BRACKET AS GUIDE TO DRILL 13 DIAMETER HOLE IN FIBERGLASS.
- 3 TO RADIO.
- 2 SEAL AROUND ANTENNA BASE.
- 1 ROUTE CABLE ALONG A-POST, UNDER TRIM COVER.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000



FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

- 70C RADIO - SATELLITE
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 MOTORHOMES		
DO NOT SCALE DRAWING		
TITLE: ANTENNA INSTL-RADIO AND CB		
SHEET 5	PART NO 169848	REV

DRAWING NO.	FEATURE
169930-01	16L
169930-02	1PV
169930-03	1LI

RELEASE	REV DATE	DWG NO	169930
REV ZONE	REVISION RECORD	DATE	DFT-ORIG



- 12 SEE INSTL-BODY, 12V FOR ADDITIONAL INFORMATION.
- 11 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 10 COIL UP EXTRA WIRE AND TIE BACK TO LOOM.
- 9 SECURE SO WIRES DO NOT CONTACT EXHAUST.
- 8 ROUTE WIRES & CABLE OVER SPRING HANGER AT THIS POINT.
- 7 SUPPLIED WITH CHASSIS.
- 6 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
- 5 ROUTE WIRES & CABLE INSIDE TOP OF CHASSIS RAIL AT THIS POINT AND TO THE REAR.
- 4 CLAMP 83610-03-000, SCREW G39-08-12B.
- 3 CLAMP 83610-01-000, SCREW G39-08-12B.

- 2. SECURE CONDUIT 41953-09, -10, -11, -13, AND -14 OVER ALL WIRES IN CONTACT WITH SHARP EDGES.
- 1. LEGEND: WINNEBAGO:-----CABLE: -----CHASSIS SUPPLIED WIRING.



- 1LI FRTL(FRED)22K-300HP 22.5TIRE
- 1PV WORKHORSE 24,000#-22.5 TIRE
- 16L FORD 22,000#-22.5 AL WHL
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

COPYRIGHT 2009 WINNEBAGO INDUSTRIES, INC.	
INDUSTRIES	
DFT-ORIG	ORIG. DATE
CHGR	ALL DIMENSIONS ARE IN MILLIMETERS
P.E.	FIRST USED
M.E.	10 J&K32H
DSNR	UNSPECIFIED TOLERANCES ARE:
WHOLE DIM (X) ± 3	
ONE-PLACE (X.X) ± 1.5	
TWO-PLACE (X.XX) ± 0.50	
ANGLE ± 1°	
THIRD ANGLE PROJECTION	

DO NOT SCALE DRAWING	
TITLE: WIRING INSTL-CHASSIS	
SHEET 1 OF 6	PART NO 169930
REF: 1	

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000



- 12 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 11 SEE INSTL-BODY,12V FOR ADDITIONAL INFORMATION.
- 10 COIL UP EXTRA WIRE AND TIE BACK TO LOOM.
- 9 SECURE SO WIRES DO NOT CONTACT EXHAUST.
- 8 ROUTE WIRES & CABLE OVER SPRING HANGER AT THIS POINT.
- 7 SUPPLIED WITH CHASSIS.
- 6 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
- 5 ROUTE WIRES & CABLE INSIDE CHASSIS RAIL AT THIS POINT AND TO THE REAR.
- 4 CLAMP 83610-03-000, SCREW G39-08-12B.
- 3 CLAMP 83610-01-000, SCREW G39-08-12B.

2. SECURE CONDUIT 41953-09, -10, -11, -13, AND -14
OVER ALL WIRES IN CONTACT WITH SHARP EDGES.

1. LEGEND: ~~WINNEBAGO~~: ~~-----~~ CABLE: ~~----~~ CHASSIS SUPPLIED WIRING.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

	FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000
---	--

1PV WORKHORSE 24,000#-22.5 TIRE

265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265 1PV



FIRST USED

10 J&K32H

DO NOT SCALE DRAWING

TITLE: **WIRING INSTL-CHASSIS**

SHEET 2	PART NO 169930	REV
---------	--------------------------	-----



- 12 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 11 SEE INSTL-BODY,12V FOR ADDITIONAL INFORMATION.
- 10 COIL UP EXTRA WIRE AND TIE BACK TO LOOM.
- 9 SECURE SO WIRES DO NOT CONTACT EXHAUST.
- 8 ROUTE WIRES & CABLE OVER SPRING HANGER AT THIS POINT.
- 7 SUPPLIED WITH CHASSIS.
- 6 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
- 5 ROUTE WIRES & CABLE INSIDE CHASSIS RAIL AT THIS POINT AND TO THE REAR.
- 4 CLAMP 83610-03-000, SCREW G39-08-12B.
- 3 CLAMP 83610-01-000, SCREW G39-08-12B.

2. SECURE CONDUIT 41953-09, -10, -11, -13, AND -14 OVER ALL WIRES IN CONTACT WITH SHARP EDGES.
1. LEGEND: — WINNEBAGO — CABLE: — CHASSIS SUPPLIED WIRING.

NOTES:





FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 1LI FRTL(FRED)22K-300HP 22.5TIRE
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265 1PV

FIRST USED		
10 J&K32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-CHASSIS		
SHEET 3	PART NO 169930	REV



- 7 CLAMP WORKHORSE ENGINE HARNESS TO CAB DECK TO PROTECT HARNESS FROM DAMAGE.
- 6 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
- 5 SECURE SO WIRES DO NOT CONTACT EXHAUST.
- 4 SUPPLIED WITH CHASSIS.
- 3 COVER WITH CONDUIT 41953-10-000 AND 41953-11-000 AS REQUIRED.

2. SECURE CONDUIT 41953-09, -10, -11, -13, AND -14 OVER ALL WIRES IN CONTACT WITH SHARP EDGES.

1. LEGEND: — WINNEBAGO — CABLE: — CHASSIS SUPPLIED WIRING.

NOTES:



- 9 CUT CHASSIS SUPPLIED BATTERY CABLE 700MM FROM BATTERY TERMINAL AND ADD TERMINAL 8348-01-000 TO CUT END
- 8 CUT CHASSIS SUPPLIED POSITIVE BATTERY CABLE 150MM FROM BATTERY TERMINAL END, DISCARD TERMINAL END AND ADD TERMINAL 113738-01-000 TO CUT END. COIL EXCESS ALONG FRAME RAIL JUST BEHIND THE RADIATOR AND TIE UP WITH WIRE-TIE 8343-04-000

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 1PV WORKHORSE 24,000#-22.5 TIRE
- 16L FORD 22,000#-22.5 AL WHL
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J&K32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-CHASSIS		
SHEET 4	PART NO 169930	REV



- 4 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 3 SEE WIRING INSTL-FRONT END FOR ADDITIONAL INFORMATION.
2. SECURE CONDUIT 41953-09, -10, -11, -13, AND -14 OVER ALL WIRES IN CONTACT WITH SHARP EDGES.
1. LEGEND: — WINNEBAGO; - - - - - CABLE; - - - - - CHASSIS SUPPLIED WIRING.

NOTES:

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000


1LI FRTL(FRED)22K-300HP 22.5TIRE

265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265 1LI

FIRST USED		
10 J&K32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-CHASSIS		
SHEET 5	PART NO 169930	REV



- NOTES:
1. LEGEND: WINNEBAGO; CABLE; CHASSIS SUPPLIED WIRING.
 2. SECURE CONDUIT 41953, TAB AS REQUIRED, OVER ALL WIRES IN CONTACT WITH SHARP EDGES.
 3. WIRE ASM-SLIDEOUT IS ROUTED AND CLAMPED WITH WIRE ASM-CHASSIS.

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

- 1LI FRTL(FRED)22K-300HP 22.5TIRE
1PV WORKHORSE 24,000#-22.5 TIRE
16L FORD 22,000#-22.5 AL WHL
265 CODES/STANDARDS-CSA/CMVSS
1B1 CODES/STANDARDS USA

1B1 265 16L 1PV 1LI

FIRST USED		
10 J&K32H		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-CHASSIS		
SHEET 6	PART NO 169930	REV

8

7

6

5

4

3

2

1

DRAWING NO.	FEATURES	SHEETS
169929-01	1PS1PV	1,2,4
169929-02	16L16Z	1,3,4
169929-03	1PS1PV	1,2,5
169929-04	16L16Z	1,3,5

2

2

	J32H	J35Z	J37F	J38N	J35P	
CABLE ASM-CHASSIS GND EXT (BLK)	16Z16L	133566-12-031	133566-12-019	133566-12-043	133566-12-047	133566-12-031
CABLE ASM-CHASSIS POWER EXT (RED)	16Z16L	141415-32-033	141415-32-020	141415-32-045	141415-32-049	141415-32-033
CABLE ASM-CHASSIS BATTERY DISCONNECT SUPPLY (RED)	16Z16L	141415-32-011	141415-32-010	141415-32-011	141415-32-010	141415-32-011
CABLE ASM-STARTER (RED)	1PS1PV	141415-35-038	141415-35-026	141415-35-050	141415-35-054	141415-35-038
CABLE ASM-COACH BATTERY (YEL)		141416-52-012	141416-52-008	141416-52-012	141416-52-008	141416-52-012
CABLE ASM-COACH BATTERY GND (BLK)		133567-12-006	133567-12-006	133567-12-006	133567-12-006	133567-12-006
CABLE ASM-CHASSIS BATTERY DISCONNECT RETURN (PUR)		141415-12-012	141415-12-006	141415-12-012	141415-12-006	141415-12-012
CABLE ASM-GENERATOR (GRN)	32I52P	141415-42-065	141415-42-085	141415-42-075	141415-42-066	141415-42-075
WIRE ASM-INVERTER	40D	154845-01-012	154845-01-020	154845-01-012	154845-01-018	154845-01-012
LEVELING SYSTEM POWER CABLE (BLU)	60M	141415-22-049	141415-22-037	141415-22-061	141415-22-070	141415-22-049
LEVELING SYSTEM GND CABLE (BLK)	60M	133566-11-008	133566-11-008	133566-11-008	N/A	133566-11-008
CHASSIS SUPPLIED POSITIVE CABLE CHASSIS BATTERY DISCONNECT SUPPLY (RED)	1PS1PV	1100	900	1100	900	1100

1

3

3

LOCATE CHASSIS SUPPLIED POSITIVE CABLE. REDUCE LENGTH TO DIMENSIONS IN COLUMN AND ADD TERMINAL 68070-01-000 TO THE CUT END 1800MM CHASSIS SUPPLIED LENGTH.

2

USED ON J32H, J35P, & J37F.

1

BATTERY CABLES MUST BE INSTALLED TO STARTER MOTOR BEFORE ENGINE WIRING HARNESS AND ROUTED IN SUCH A MANNER AS TO PREVENT ANY POSSIBLE DEGRADATION FROM THE EXHUAUST SYSTEM.

NOTES:

8

7

6

5

4

3

2

1

RELEASE

REV

DATE

DWG NO

169929

REV

ZONE

REVISION RECORD

DATE

DFTR.ORG

52P

GEN-5.5KW ONAN-GAS-MARQ GOLD

32I

GENERATOR PREP KIT

60M

HYDRAULIC LEVEL JACKS-AUTO

40D

INVERTER-DC/AC,600 WATT

1PV

WORKHORSE 24,000#-22.5 TIRE

1PS

WORKHORSE 22,000#-22.5 TIRE

16Z

FORD 24,000#-22.5 ALUM WHEEL

16L

FORD 22,000#-22.5 AL WHL

265

CODES/STANDARDS-CSA/CMVSS

1B1

CODES/STANDARDS USA

1B1

265

WINNEBAGO

INDUSTRIES

COPYRIGHT 2009

WINNEBAGO

INDUSTRIES, INC.

DFTR

CHKR

P.E.

M.E.

DSNR

ORIG. DATE

ALL DIMENSIONS ARE IN MILLIMETERS

FIRST USED

10 J-SERIES

UNSPECIFIED TOLERANCES ARE:

WHOLE DIM (X) ± 3

ONE-PLACE (X.X) ± 1.5

TWO-PLACE (X.XX) ± 0.50

ANGLE ± 1°

MATERIAL:

THIRD ANGLE PROJECTION

DO NOT SCALE DRAWING

TITLE:

BATTERY INSTL

SHEET1 OF 5


PART NO169929

REV

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

X-X

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000



- 7 SEE LEVELING SYSTEM INSTL FOR ADDITIONAL INFORMATION.
- 6 SEE CHASSIS ELECTRICAL BOX ASM FOR ADDITIONAL INFORMATION.
- 5 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL INFORMATION.
- 4 USE TWO NUTS HERE TO ACCOUNT FOR BATTERY HEIGHT DIFFERENCE.
- 3 USED ON J32H, J35P, & J37F.
- 2 LOCATE CHASSIS SUPPLIED CABLE REDUCE CABLE TO 700MM AND ADD TERMINAL 8348-01-000 TO THE CUT END.
- 1 CABLE WILL BE ROUTED TO THE RIGHT SIDE OF STEP BOX ON THE F32H. SEE SHT.5


NOTES:

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 40D INVERTER-DC/AC,600 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE: BATTERY INSTL		
SHEET 2	PART NO 169929	REV



- 7 CABLE WILL BE ROUTED TO THE RIGHT SIDE OF STEP BOX ON THE F32H. SEE SHT.5
- 6 SEE CHASSIS ELECTRICAL BOX ASM FOR ADDITIONAL INFORMATION.
- 5 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL INFORMATION.
- 4 USE TWO NUTS HERE TO ACCOUNT FOR BATTERY HEIGHT DIFFERENCE.
- 3 SEE LEVELING SYSTEM INSTL FOR ADDITIONAL INFORMATION.
- 2 LOCATE CHASSIS SUPPLIED GROUND WIRES TO CABLE, AND REDUCE LENGTH TO 700MM AND ADD TERMINAL 8348-01-000 TO THE CUT END.
- 1 USED ON J32H, J35P, & J37F.


NOTES:

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 40D INVERTER-DC/AC,600 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE: BATTERY INSTL		
SHEET 3	PART NO 169929	REV



265 CODES/STANDARDS-CSA/CMVSS


1B1 CODES/STANDARDS USA

1B1 265

FIRST USED		
10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE: BATTERY INSTL		
SHEET4	PART NO 169929	REV

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000



2 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL INFORMATION.
1 SEE CHASSIS ELECTRICAL BOX ASM FOR ADDITIONAL INFORMATION.

NOTES:


- 40D INVERTER-DC/AC,600 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265

FIRST USED		
10 J-FREIGHTLINER		
DO NOT SCALE DRAWING		
TITLE: BATTERY INSTL,FL		
SHEET 2	PART NO 171067	REV

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000



265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265

FIRST USED

10 J-FREIGHTLINER

DO NOT SCALE DRAWING

TITLE:

BATTERY INSTL,FL

SHEET 3

PART NO

171067


REV

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

DRAWING NO.	SHEETS	UNITS
171695-01	1,2,3	J32H,K32H
171695-02	4,5,6	J37F,K35P

RELEASE	REV A	DATE	DWG NO 171695
REV ZONE	REVISION RECORD		DATE Dftr-Orig



52N AWNING - PATIO, ELECTRIC

29Q SOLAR PANEL-10 WATT

265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265

WINNEBAGO INDUSTRIES

COPYRIGHT 2009
WINNEBAGO
INDUSTRIES, INC.

Dftr	ORIG. DATE
CHGR	
P.E.	ALL DIMENSIONS ARE IN MILLIMETERS
M.E.	FIRST USED
DSNR	10 J&K-SERIES

UNSPECIFIED TOLERANCES ARE:

WHOLE DIM (X)	± 3
ONE-PLACE (X.X)	± 1.5
TWO-PLACE (X.XX)	± 0.50
ANGLE	± 1°

THIRD ANGLE
PROJECTION

DO NOT SCALE DRAWING

TITLE:
CHASSIS ELECTRICAL BOX ASM

SHEET 1 OF 6 PART NO 171695 REV

REF: 1 10/24/2009

D

C

B


A

D


C

B

A



VIEW BA



VIEW BB


- NOTES:
- 7 WIRE MARKED WITH 2 WRAPS OF YELLOW TAPE.
 - 6 WIRE MARKED WITH PURPLE TAPE.
 - 5 WIRE MARKED WITH YELLOW TAPE.
 - 4 WITHOUT 52N
 - 3 USE THE LONGER SCREW TO PROPERLY ATTACH BREAKER TO BUSS BAR.
 - 2 REPLACE EXISTING SCREW TO PROPERLY ATTACH BREAKER TO BUSS BAR.
 - 1 IF CIRCUIT NOT USED, TAPE BACK TO HARNESS.

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

- 32W GENERATOR START,AUTO-SYSTEM
- 52N AWNING - PATIO, ELECTRIC
- 29Q SOLAR PANEL-10 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J&K-SERIES		
DO NOT SCALE DRAWING		
TITLE: CHASSIS ELECTRICAL BOX ASM		
SHEET 2	PART NO 171695	REV



- 9 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL IFORMATION.
- 8 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 7 SEE WIRING INSTL-BODY,12V FOR ADDITIONAL INFORMATION.
- 6 WIRE MARKED WITH PURPLE TAPE.
- 5 WIRE MARKED WITH YELLOW TAPE.
- 4 INSERT CIRCUIT LJ, UUA, LK, OR UUG INTO UNDERSIDE OF FUSE HOLDER & INSTALL FUSE.
- 3 SECURE WITH SOLENOID MOUNTING SCREW.

2. SECURE CONDUIT 41953, TAB AS REQUIRED, OVER ALL WIRES IN CONTACT WITH SHARP EDGES.

1. LEGEND: — WINNEBAGO, - - - - - CABLE, - - - - - CHASSIS SUPPLIED WIRING.

NOTES:

- 52N AWNING - PATIO, ELECTRIC
- 29Q SOLAR PANEL-10 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265


FIRST USED		
10 J&K-SERIES		
DO NOT SCALE DRAWING		
TITLE: CHASSIS ELECTRICAL BOX ASM		
SHEET 3	PART NO 171695	REV

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

8	7	6	5	4	3	2	1
DRAWING NO.	SHEETS	UNITS					
172796-01	1,2,3	J32H					
172796-02	4,5,6	J35P,J37F					

RELEASE	REV	DATE	DWG NO	172796
REV	ZONE	REVISION RECORD	DATE	DFTR-ORIG





- 52N AWNING - PATIO, ELECTRIC
- 29Q SOLAR PANEL-10 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

WINNEBAGO INDUSTRIES

COPYRIGHT 2009
WINNEBAGO
INDUSTRIES, INC.

DFTR	ORIG. DATE
CHGR	ALL DIMENSIONS ARE IN MILLIMETERS
P.E.	
M.E.	FIRST USED
DSNR	10 J-SERIES,FL
UNSPECIFIED TOLERANCES ARE:	MATERIAL:
WHOLE DIM (X) ± 3	
ONE-PLACE (X.X) ± 1.5	
TWO-PLACE (X.XX) ± 0.50	
ANGLE ± 1°	
THIRD ANGLE PROJECTION	

DO NOT SCALE DRAWING	
TITLE: CHASSIS ELECTRICAL BOX ASM	
SHEET 1 OF 6	PART NO 172796
REF:	1



- 7 WIRE MARKED WITH 2 WRAPS OF YELLOW TAPE.
- 6 WIRE MARKED WITH PURPLE TAPE.
- 5 WIRE MARKED WITH YELLOW TAPE.
- 4 WITHOUT 52N
- 3 USE THE LONGER SCREW TO PROPERLY ATTACH BREAKER TO BUSS BAR.
- 2 REPLACE EXISTING SCREW TO PROPERLY ATTACH BREAKER TO BUSS BAR.
- 1 IF CIRCUIT NOT USED, TAPE BACK TO HARNESS.

NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

32W	GENERATOR-START,AUTO SYSTEM
52N	AWNING - PATIO, ELECTRIC
29Q	SOLAR PANEL-10 WATT
265	CODES/STANDARDS-CSA/CMVSS
1B1	CODES/STANDARDS USA

1B1 265


10 J-SERIES, FL

DO NOT SCALE DRAWING

TITLE:

CHASSIS ELECTRICAL BOX ASM

SHEET 2	PART NO 172796	REV
---------	--------------------------	-----



- 9 SEE WIRING INSTL-CHASSIS FOR ADDITIONAL IFORMATION.
- 8 SEE BATTERY INSTL FOR ADDITIONAL INFORMATION.
- 7 SEE WIRING INSTL-BODY, 12V FOR ADDITIONAL INFORMATION.
- 6 WIRE MARKED WITH PURPLE TAPE.
- 5 WIRE MARKED WITH YELLOW TAPE.
- 4 INSERT CIRCUIT LJ & LK INTO UNDERSIDE OF FUSE HOLDER & INSTALL FUSE.
- 3 SECURE WITH SOLENOID MOUNTING SCREW.

2. SECURE CONDUIT 41953, TAB AS REQUIRED, OVER ALL WIRES IN CONTACT WITH SHARP EDGES.

1. LEGEND: — WINNEBAGO; - - - - - CABLE; - - - - - CHASSIS SUPPLIED WIRING.


NOTES:

- 52N AWNING - PATIO, ELECTRIC
- 29Q SOLAR PANEL-10 WATT
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

FIRST USED		
10 J-SERIES,FL		
DO NOT SCALE DRAWING		
TITLE:		
CHASSIS ELECTRICAL BOX ASM		
SHEET 3	PART NO 172796	REV

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000



8

7

6

5








4

3


2

1

LAMP ASM-PACKAGE,PANCAKE

NO	PART NUMBER	DESCRIPTION
LF1-1	LAMP 98024-01-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 1 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LF2-1	LAMP 98024-03-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 2 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LO1-1	LAMP 98024-05-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, OPTI CLEAR LENS, 1 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LO2-1	LAMP 98024-06-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, OPTI CLEAR LENS, 2 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LF1N1	LAMP 98024-07-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 1 BULB W/O SWITCH PROGRESSIVE DYNAMICS INC. 
LF2N1	LAMP 98024-08-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 2 BULB W/O SWITCH PROGRESSIVE DYNAMICS INC. 
LFSN1	LAMP 98024-09-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, SINGLE FROSTED LENS, 2 BULB W/O SWITCH PROGRESSIVE DYNAMICS INC. 

LAMP ASM-PACKAGE,PORCH

NO	PART NUMBER	DESCRIPTION
LEXT-1	LAMP 97917-01-CHT SCREW G67-10-129 (4) CONNECTOR 58028-01-000 (2)	LAMP ASM-PORCH, SURFACE MOUNT BARGMAN 
LEXT-2UL	LAMP 8089-01-000 SCREW G68-06-10E (2) CONNECTOR 58028-01-000 (2)	LAMP ASM-PORCH, RECESSED UL LIST JRV PROD 
LEXT-2CA	LAMP 8089-02-000 SCREW G68-06-10E (2) CONNECTOR 58028-01-000 (2)	LAMP ASM-PORCH, RECESSED CAN LIST JRV PROD 
LEXT-3	LAMP 171513-01-CHT SCREW G67-10-129 (2) CONNECTOR 58028-01-000 (2)	LAMP ASM-PORCH SURFACE MOUNT OPTRONICS

87.0

22.2 R

96

CUT OUT IN PANEL

HALOGEN LAMP

LINE SPRING CLIPS UP WITH RELIEF IN CUT OUT

DETAIL CA

LEGEND

PART NUMBER

QUANTITY

XXXX

XX

PART NUMBER

QUANTITY

XXXXXX

XX

FIRST USED

96 MH'S

DO NOT SCALE DRAWING

TITLE:

PART LISTING-ELECTRICAL

SHEET 3





PART NO121339

REV





DWG NO121339

2/17/2010

LAMP ASM-PACKAGE,PANCAKE

NO	PART NUMBER	DESCRIPTION
LF1-2	LAMP 137417-01-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 1 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LF2-2	LAMP 137417-04-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 2 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LO1-2	LAMP 137417-02-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, OPTI CLEAR LENS, 1 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LO2-2	LAMP 137417-05-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, OPTI CLEAR LENS, 2 BULB W/SWITCH PROGRESSIVE DYNAMICS INC. 
LF1N2	LAMP 137417-03-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)	LAMP ASM, FROSTED LENS, 1 BULB W/O SWITCH PROGRESSIVE DYNAMICS INC. 
LFSN2	LAMP 137417-06-CHT SCREW G11-08-16U (6) CONNECTOR 58028-01-000 (2)	LAMP ASM, SINGLE FROSTED LENS, 2 BULB W/O SWITCH PROGRESSIVE DYNAMICS INC. 

LAMP ASM-PACKAGE,HALOGEN

NO	PART NUMBER	DESCRIPTION
HAL	LAMP 123775-01-CHT SCREW (SUPPLIED) CONNECTOR 58028-01-000 (2)	LAMP ASM-HALOGEN, READING 1 BULB 
HAL-S	LAMP 123775-01-CHT SPACER 123775-02-CHT SCREW G13-06-16U (3) CONNECTOR 58028-01-000 (2)	LAMP ASM-HALOGEN, READING WITH 3/4" SPACER 1 BULB 
HAL-2	LIGHT-HAL,ROUND 165170-01-CHT SCREW G13-06-12B (2) CONNECTOR 58028-01-000 (2)	LIGHT-HALOGEN, ROUND 3" 
HAL-4	LIGHT-HAL,ROUND 165643-01-CHT SCREW G13-05-16B (3) CONNECTOR 58028-01-000 (2) (SEE DETAIL CA)	LIGHT-HALOGEN, ROUND 4.5" 

8

7

6



5

4

3

2

1

8			7			6			5			4			3			2			1																																																																																																																	
LAMP ASM-PACKAGE,FLUORESCENT															LAMP ASM-PACKAGE,MAKEUP LAMP															LAMP ASM-PACKAGE,OTHER															LAMP ASM-PACKAGE,PANCAKE															DWG NO 121339																																																																										
NO			PART NUMBER						DESCRIPTION						NO			PART NUMBER						DESCRIPTION						NO			PART NUMBER						DESCRIPTION																																																																																															
FLU-1			LAMP 91936-02-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/SWITCH THIN-LITE						LMU3-1			LAMP 110235-01-CHT SCREW W/SPACER (SUPPLIED) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 3 BULB (SUPPLIED) PROGRESSIVE DYNAMICS						LSH-1			LAMP 121935-01-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-SHOWER PROGRESSIVE DYNAMICS INC.						LF1-3			LAMP 170693-01-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, FROSTED LENS, 1 BULB W/SWITCH GUSTAFSON																																																																																
FLU-2			LAMP 91936-01-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB W/SWITCH THIN-LITE						LMM3-2			LAMP 123774-03-CHT SCREW (SUPPLIED) BULB 123918-01-000 (3) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/MIRROR) 3 BULB GUSTOFSON						LSH-2			LAMP 164039-01-CHT SCREW G11-08-16U (3) CONNECTOR 58028-01-000 (2)						LIGHT-DOME,SHOWER						LF2-3			LAMP 170693-04-CHT SCREW G11-08-24U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, FROSTED LENS, 2 BULB W/SWITCH GUSTAFSON																																																																																
FLU-3			LAMP 127327-01-CHT SCREW G11-08-12U (2) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 1-12" BULB W/SWITCH THIN-LITE						LMU3-2			LAMP 138116-01-CHT SCREW (SUPPLIED) BULB 123918-01-000 (3) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 3 BULB GUSTOFSON						LSH-3			LAMP 164040-01-CHT SCREW G13-07-12U (3) CONNECTOR 58028-01-000 (2)						LIGHT-DOME,SHOWER GLASS						LO1-3			LAMP 170693-02-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, OPTI CLEAR LENS, 1 BULB W/SWITCH GUSTAFSON																																																																																
FLU-4			LAMP 130338-01-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB SURFACE MOUNT W/SWITCH THIN-LITE						LMU3-3			LAMP 162446-01-CHT SCREW (SUPPLIED) BULB 123918-01-000 (3) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 3 BULB GUSTOFSON						LCR-1			LAMP 61424-01-000 SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-COURTESY,AISLE RAMCO (RECTANGULAR)						L02-3			LAMP 170693-05-CHT SCREW G11-08-24U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, OPTI CLEAR LENS, 2 BULB W/SWITCH GUSTAFSON																																																																																
FLU-5			LAMP 153464-02-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/SWITCH COOL WHITE BULB THIN-LITE						LMU4-1			LAMP 110235-02-CHT SCREW G11-08-16U (2) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 4 BULB PROGRESSIVE DYNAMICS						LCS-1			LAMP 108354-01-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-COURTESY,AISLE ITC MARINE (SQUARE)						LF1N3			LAMP 170693-03-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, FROSTED LENS, 1 BULB W/O SWITCH GUSTAFSON																																																																																
FLU-6			LAMP 130338-02-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB SURFACE MOUNT WARM WHITE BULB W/SWITCH THIN-LITE						LMU4-2			LAMP 138116-02-CHT SCREW (SUPPLIED) BULB 123918-01-000 (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 4 BULB GUSTOFSON						READ-1			LIGHT-READING 132427-01-CHT SCREW SUPPLIED W/ LIGHT CLIP-U 141395-02-CHT (2) CONNECTOR 58028-01-000 (2)						LIGHT-READING,SWIVEL,ROUND 1 BULB						LFSN3			LAMP 170693-06-CHT SCREW G11-08-24U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, SINGLE FROSTED LENS, 2 BULB W/O SWITCH GUSTAFSON																																																																																
FLU-7			LAMP 153464-05-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/SWITCH WARM WHITE BULB THIN-LITE						LMU4-3			LAMP 162446-02-CHT SCREW (SUPPLIED) BULB 123918-01-000 (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/O MIRROR) 4 BULB GUSTOFSON						READ-2			LIGHT-READING 128786-02-CHT SCREW G11-08-16J (2) BULB 123917-01-000 CONNECTOR 58028-01-000 (2)						LIGHT,READING,SWIVEL						LOS N3			LAMP 170693-07-CHT SCREW G11-08-24U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, OPTICLEAR LENS, 2 BULB W/O SWITCH GUSTAFSON																																																																																
FLU-8			LAMP 173072-01-CHT SCREW G11-08-12U (2) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" ONE 8 WATT BULB W/SWITCH OPTRONICS						LMM4-2			LAMP 123774-01-CHT SCREW G11-08-16U (2) BULB 123918-01-000 (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-MAKEUP (W/MIRROR) 4 BULB GUSTOFSON						READ-3			LIGHT-READING 170833-01-CHT SCREW SUPPLIED W/LIGHT CONNECTOR 58028-01-000 (2)						LIGHT,READING,HAL						LO1N3			LAMP 170693-08-CHT SCREW G11-08-16U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM, OPTICLEAR LENS, 1 BULB W/O SWITCH GUSTAFSON																																																																																
FLUN1			LAMP 91936-04-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/O SWITCH THIN-LITE																																																																																																																													
FLUN2			LAMP 91936-03-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB W/O SWITCH THIN-LITE																																																																																																																													
FLUN3			LAMP 153464-01-CHT SCREW G11-08-12U (4) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/O SWITCH COOL WHITE BULB THIN-LITE																																																																																																																													
FLUN4			LAMP 153464-03-CHT SCREW G11-08-12U (6) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB W/O SWITCH COOL WHITE BULB THIN-LITE																																																																																																																													
FLUN5			LAMP 153464-06-CHT SCREW G11-08-12U (6) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 18" 2 BULB W/O SWITCH WARM WHITE BULB THIN-LITE																																																																																																																													
FLUN6			LAMP 153464-04-CHT SCREW G11-08-12U (6) CONNECTOR 58028-01-000 (2)						LAMP ASM-FLUORESCENT 12" 2 BULB W/O SWITCH WARM WHITE BULB THIN-LITE																																																																																																																													
																														LEGEND																																																																																																								
																																																																																																																																						

87654321

DWG NO121339

ANTENNA ASM-PACKAGE

NO	PART NUMBER	DESCRIPTION
ANT-1	ANTENNA 76319-24-000 HARDWARE-INTERIOR 76319-25-000 BUMPER 69726-02-000 (2) CLIP 80734-02-000	ROOF MOUNT TV ANTENNA ASM 25.5" MAST 600 MAX COAX LENGTH
ANT-2	ANTENNA 076319-23-000(UP TO 05-31-09) 173519-01-CHT(AFTER 06-01-09) HARDWARE-INTERIOR 76319-25-000 BUMPER 69726-02-000 (2) ADAPTER SUPPLIED W/ANTENNA	ROOF MOUNT TV ANTENNA ASM 44.5" MAST 600 MAX COAX LENGTH
ANT-2W	ANTENNA 076319-23-000(UP TO 05-31-09) 173519-01-CHT(AFTER 06-01-09) HARDWARE-INTERIOR 76319-25-000 BUMPER 69726-02-000 (2) ADAPTER SUPPLIED W/ANTENNA WEDGE 76319-26-000	ROOF MOUNT TV ANTENNA ASM 44.5" MAST 600 MAX COAX LENGTH
ANTA-1	ANTENNA 158270-01-CHT BUMPER 69726-02-000 (2) ADAPTER SUPPLIED W/ANTENNA ANTENNA-WINGMAN, ACCESSORY 173519-03-CHT	ROOF MOUNT TV ANTENNA ASM AUTOMATIC 600 MAX COAX LENGTH
ANT-3	ANTENNA-TV ROOF MNT.ROUND 167632-01-CHT PLATE-ROOF, CABLE ENTRY 146488-01-000 SCREW G67-10-129 (10) CABLE ASM-COAX 87105-01-006 ADAPTER 82134-01-000	ROOF MOUNT OMNI- DIRECTIONAL ANTENNA MOUNTING SCREWS SUPPLIED WITH ANTENNA 600 MAX COAX LENGTH
ANT-4	ANTENNA 173519-01-CHT HARDWARE-INTERIOR 76319-25-000 BUMPER 69726-02-000 (2) ADAPTER SUPPLIED W/ANTENNA ANTENNA-HANDLE EXTENSION 173519-02-CHT	ROOF MOUNT TV ANTENNA ASM 44.5" MAST 600 MAX COAX LENGTH

ANTENNA ASM-PACKAGE

ANTEXT-1	CABLE ASM-EXTENS 77069-02-000	RADIO ANTENNA CABLE EXTENSION 2400MM USABLE LENGTH
ANTKIT-1	ADAPTER-PLATE 76319-06-000 SCREW G11-08-08T (6) CLIP-WIRE 80734-02-000 SCREW G11-08-08T	PLATE ASM-ADAPTERS CABLE ROOF MOUNTING PLATE W/ CABLE-CABLE ADAPTER, FITTINGS, AND CABLE RETAINING CLIP
ANT-R	ANTENNA-RADIO 90944-01-000 EXTENDER-SHAFT ANTENNA 109889-04-000 BRACKET-ANTENNA GROUND 147741-01-CHT	ROOF MOUNT RADIO ANTENNA
ANTEXT-2	CABLE ASM-EXTENS 77069-03-000	RADIO ANTENNA CABLE EXTENSION 6600 MM USABLE LENGTH
ANT-A	ANTENNA-RADIO 90944-01-000 EXTENDER-SHAFT 76 MM 171825-01-000 (2) BRACKET-GROUND 147741-01-CHT NUT OMD01K-06-000 (2)	ROOF MOUNT RADIO ANTENNA THICK ROOF

SATELLITE DISH INSTL

DM-1	SATELLITE DISH 137135-02-000 SCREW G67-10-12B (8) PLATE & BRACKET (SUPPLIED) SCREW G67-10-12B (10)	SATELLITE DISH ANTENNA ASM MANUAL SETUP
DA-1	SATELLITE DISH 163598-01-CHT PLATE-ROOF,CABLE ENTRY QUAD 146488-03-000 SCREW G67-10-12U (8) (FOR PLATE) SCREW G39-10-12U (12) (FOR SATELLITE DISH)	SATELLITE DISH ANTENNA ASM AUTOMATIC SETUP
DI-1	SATELLITE DISH 154474-04-CHT SCREW G39-10-12B (12) PLATE 146488-01-000 SCREW G67-10-12B (10)	SATELLITE DISH ANTENNA ASM IN MOTION SETUP

SATELLITE DISH INSTL

DA-2	SATELLITE DISH 163598-01-CHT PLATE-ROOF,CABLE ENTRY QUAD 146488-03-000 CABLE ASM-COAX 9" 163598-04-000 ADAPTOR-CABLE TO CABLE 82134-01-000 SCREW G67-10-12U (8) (FOR PLATE) SCREW G39-10-12U (12) (FOR SATELLITE DISH)	SATELLITE DISH ANTENNA ASM AUTOMATIC SETUP
DI-2	SATELLITE DISH 154474-04-CHT PLATE-ROOF,CABLE ENTRY QUAD 146488-03-000 CABLE ASM-COAX 9" 163598-04-000 ADAPTOR-CABLE TO CABLE 82134-01-000 SCREW G67-10-12U (8) (FOR PLATE) SCREW G39-10-12U (12) (FOR SATELLITE DISH)	SATELLITE DISH ANTENNA ASM AUTOMATIC SETUP
DM-2	SATELLITE DISH 137135-05-000 PLATE-ROOF,ENTRY (SUPPLIED WITH SATELLITE DISH) SCREW G67-10-12U (8) (FOR ROOF PLATE) SCREW G67-10-12U (10) (FOR SATELLITE DISH)	SATELLITE DISH ANTENNA ASM MANUAL SETUP

SENSORS

LPGD	LP GAS DETECTOR 150138-03-CHT SCREW G68-06-10U (2)	DETECTOR-LP GAS
------	---	---------------------

PANELS

SOLAR	PANEL-SOLAR 10 WATT 151647-01-000 (UP TO 03-14-10) 176161-01-000 (AFTER 03-15-10) SCREW G11-08-12U (4)	SOLAR PANEL
-------	--	-----------------

LEGEND

PART NUMBER

QUANTITY

PART NUMBER

QUANTITY

1

ADD BUMPER TO BOTTOM SIDE OF ANTENNA WINGS TO PREVENT DAMAGE TO ROOF.

87654321

96 MH'S

DO NOT SCALE DRAWING

PART LISTING-ELECTRICAL

SHEET 5

PART NO121339



REV

2/17/2010



87654321

DWG NO121339






RECEPTACLE PACKAGE-GFI

NO	PART NUMBER	DESCRIPTION
<u>GFI</u> US	RECEPTACLE 163319-01-CHT BOX 91910-02-000 WIRE-BONDING 133678-03-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 TUBING-VINYL 8041-02-000 (300MM) ¹	GFI RECEPTACLE WITH COVER AND BOX FOR US APPLICATION 
<u>GFI</u> CAN	RECEPTACLE 163319-01-CHT BOX 91910-01-000 WIRE-BONDING 133678-03-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 TUBING-VINYL 8041-02-000 (300MM) ¹	GFI RECEPTACLE WITH COVER AND BOX FOR CANADA APPLICATION 

RECEPTACLE PACKAGE-GFI


NO	PART NUMBER	DESCRIPTION
<u>GFI-1</u> US	RECEPTACLE 163319-01-CHT BOX 133070-01-000 WIRE-BONDING 133678-03-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 TUBING-VINYL 8041-02-000 (300MM) ¹	GFI RECEPTACLE WITH COVER AND BOX FOR US APPLICATION 
<u>GFI-1</u> CAN	RECEPTACLE 163319-01-CHT BOX 133070-02-000 WIRE-BONDING 133678-03-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 TUBING-VINYL 8041-02-000 (300MM) ¹	GFI RECEPTACLE WITH COVER AND BOX FOR CANADA APPLICATION 

SPACERS



NO	PART NUMBER	DESCRIPTION
SP-01	SPACER 102568-01-XXX	STANDARD 110V RECEPTACLE SPACER (WOOD,VYL RAP,OG) 
SP-02	SPACER 102568-02-XXX	WOOD SPACER FOR CEILING MOUNTED A/C PREP BOX (US) (WOOD,VYL RAP,OG) 
SP-03	SPACER 102568-03-XXX	WOOD SPACER FOR CEILING MOUNTED A/C PREP BOX (CANADA) (WOOD,VYL RAP,OG) 
SP-04	SPACER 133713-01-CHT	STANDARD 110V RECEPTACLE SPACER (WOOD,VYL RAP,BEV) 
SP-05	SPACER 133713-20-XXX	STANDARD 110V RECEPTACLE SPACER (WOOD,BEV) 

SP-21

SPACER
126052-01-XXX

WOOD SPACER FOR 1 - 110V
RECEPTACLE AND 1 - REAR TV
(12V) JACK
(WOOD,BEV)


LEGEND

MISC.	SPACER
PART NUMBER LISTING 	 PART NUMBER

NOTES:

1

APPLY TUBING TO BARE GROUND WIRES.

FIRST USED

96 MH'S

DO NOT SCALE DRAWING

TITLE:
PART LISTING-ELECTRICAL

SHEET 6

PART NO121339

REV

87654321

2/17/2010

87654321

D

C



B

A


1

DWG NO121339


PREP-A/C, RECESSED (W/OUT FACTORY A/C)

NO	PART NUMBER	DESCRIPTION
PREP A/C-US	BOX 91910-02-000 COVER 84099-02-CHT LABEL 91243-01-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 (3)	BOX AND EQUIPMENT USED FOR A/C PREP (W/OUT FACTORY A/C). US APPLICATION (RECESSED IN ROOF) 
PREP A/C-CAN	BOX 91910-01-000 COVER 84099-02-CHT LABEL 91243-01-000 SCREW G13-07-12B (4) CONNECTOR 8313-01-000 (3)	BOX AND EQUIPMENT USED FOR A/C PREP (W/OUT FACTORY A/C). CANADA APPLICATION (RECESSED IN ROOF) 


CONNECTION BOX-POWER CORD

NO	PART NUMBER	DESCRIPTION
J-PC 30	BOX 8289-01-000 COVER 8294-01-000 SCREW G67-10-10B (2) WIRE ASM-GROUND 133678-02-000 CONNECTOR 8314-01-000 (3) CONNECTOR 8356-02-000 CONNECTOR (PC) 8355-01-000	CONNECTION BOX IN POWER CORD COMPT FOR POWER CORD (US & CA APPLICATION) 
J-PC 30-US		
J-PC 30-CA		


CONNECTION BOX-GENERATOR RECEPTACLE

NO	PART NUMBER	DESCRIPTION
J-RCP 30	BOX 8289-01-000 RECEPTACLE 24924-02-000 COVER 69238-01-000 SCREW G67-10-10B (2) WIRE ASM-GROUND 133678-02-000 133678-04-000 CONNECTOR 8314-01-000 TUBING-VINYL 8041-02-000 (150MM)	CONNECTION BOX IN POWER CORD COMPT FOR THE GENERATOR RECEPTACLE (US & CA APPLICATION) 
J-RCP 30-US		
J-RCP 30-CA		

CONNECTION BOX, GENERATOR SERVICE FEED

NO	PART NUMBER	DESCRIPTION
J-GEN 30	BOX 8289-01-000 COVER 8294-01-000 SCREW G67-10-10B (2) WIRE ASM-GROUND 133678-02-000 WIRE NUT-GREY 8314-01-000 (3) CONNECTOR-WIRE 8356-01-000	BOX AND EQUIPMENT USED FOR CONNECTING THE GENERATOR LEADS TO THE SERVICE ENTRANCE WIRES (US & CA APPLICATION) 
J-GEN 30-US		
J-GEN 30-CA		

PREP-A/C, SURFACE (W/OUT FACTORY A/C)

NO	PART NUMBER	DESCRIPTION
PREP SURF	BOX 93603-01-000 COVER 53337-01-000 LABEL 91243-01-000 WIRE-BONDING 8019-01-000 SCREW G11-08-12B (2) TERMINAL 8328-01-000 CONNECTOR 8313-01-000 (2) CONNECTOR 8311-01-000	SURFACE MOUNT, US AND CANADA, BOX AND EQUIPMENT FOR A/C PREP (W/OUT FACTORY A/C). TYPICALLY LOCATED ON OVERHEAD CABINET INNER WALL OR ON CEILING. 

LEGEND

PART NUMBER

LISTING

XXXX

XX

NOTES:

1 APPLY TUBING TO BARE GROUND WIRES.

96 MH'S

DO NOT SCALE DRAWING


TITLE: PART LISTING-ELECTRICAL

SHEET 7PART NO121339REV


87654321

↑

12/17/2010



LAMP-MARKER,BASE
147680-01-01A
LAMP-MARKER,LENS,AMBER
147680-02-01A
SCREW
000G11-08-12B (EXT) (2)



LAMP-MARKER,BASE
147680-01-01A
LAMP-MARKER,LENS,AMBER
147680-02-01A
SCREW
000G11-08-12B (EXT) (2)


FOR ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265



COPYRIGHT 2010
WINNEBAGO
INDUSTRIES, INC.

DFT-ORIG	ORIG. DATE
CHKR	
P.E.	ALL DIMENSIONS ARE IN MILLIMETERS
M.E.	FIRST USED
DSNR	10 J-SERIES
UNSPECIFIED TOLERANCES ARE:	MATERIAL:
WHOLE DIM (X) ± 3	
ONE-PLACE (X.X) ± 1.5	
TWO-PLACE (X.XX) ± 0.50	
ANGLE ± 1°	
THIRD ANGLE PROJECTION	

DO NOT SCALE DRAWING

TITLE: WIRING INSTL-EXTERIOR LAMPS			
SHEET 1 OF 3	PART NO	171037	REV

1 NOT USED ON SHELLS.

LAMP ASM-MARKER,BASE
147680-01-01A (5)
LAMP ASM-MARKER,LENS,AMBER
147680-02-01A (5)
SCREW
000G39-08-08T (EXT)(10)

WIRE ASM-CLEARANCE LAMPS
129943-01-000

2 PIN HOUSING TO
WIRE ASM-IP,MAIN

16L 16Z
WIRE ASM-HEADLAMP,FD
141678-11-000
1PS 1PV
WIRE ASM-HEADLAMP,WH
141678-13-000
1LL
WIRE ASM-HEADLAMP,
FRED LEFT
141678-15-000 (UP TO 01-12-10)
141678-17-000 (AFTER 01-13-10)
WIRE ASM-HEADLAMP,
FRED RIGHT
141678-16-000 (UP TO 01-12-10)
141678-18-000 (AFTER 01-13-10)

LAMP-CLEARANCE,RED
102520-02-000 (5)
SCREW
000G39-08-16T (10)
GASKET
102541-01-000 (5)
BULB
036196-01-000 (5)

WIRE ASM-
TAILLAMPS
149622-07-000(UP TO 11-01-09)
149622-10-000(AFTER 11-02-09)
149622-08-000(UP TO 11-01-09)
149622-11-000(AFTER 11-02-09)
149622-09-000(UP TO 11-01-09)
149622-12-000(AFTER 11-02-09)

LIGHT-THIRD BRAKE,LED
151076-01-000 (2)
SCREW
000G39-06-16T (4)

LAMP ASM-STOP/TURN/TAIL
146205-02-000(2)(UP TO 11-01-09)
174698-01-000(2)(AFTER 11-02-09)
BULB
112708-01-000(2)(UP TO 11-01-09)
SCREW
000G39-08-16T(4)

LAMP ASM-STOP/TURN/TAIL
146205-01-000(2)(UP TO 11-01-09)
174698-01-000(2)(AFTER 11-02-09)
BULB
112708-01-000(2)(UP TO 11-01-09)
SCREW
000G39-08-20T(4)

LAMP-MARKER,RED
117826-01-000 (2)
GASKET-MARKER LIGHT
117826-03-000 (2)
BULB
036196-01-000 (2)
SCREW
000G11-08-12B (EXT) (4)

REFLECTOR
106646-02-000 (2)
(ADHESIVE BACKING)

LAMP ASM-BACKUP,CLEAR
152352-01-000 (2)
BULB
037934-01-000 (2)
SCREW
000G11-06-24B (8)

LAMP-LICENSE PLATE
087201-01-000
SCREW
000G11-06-12B (EXT)(2)

CONNECTOR-TRAILER
157593-01-000
SCREW
101618-01-000 (4)

2 PIN HOUSING
TO WIRE ASM-CHASSIS


TO GROUND STUD
TP,RRJ
(LOCATED ON BACKSIDE
OF GENERATOR OUTRIGGER)
NUT-GROUND
000D39-05-00B

- 6 LAMP WILL ONLY BE USED AS A TAILLAMP.
- 5 MOUNT LAMP ASM SO THAT THE LABEL TOP IS IN THE UP POSITION.
- 4 CLEAN PAINT OFF METAL (BOLT) BEFORE CONNECTING
GROUND TO INSURE CONTACT.
- 3 CONNECTOR-PLUG,TRAILER 146246-01-000 TO
BE SUPPLIED LOOSE IN COACH WITH 240
- 2 SECURE WIRE ASM APPROX. EVERY 450 TO BACKWALL BRACKETS.
USE TIE-WIRE 008343-01-000 OR 093147-01-000 AS APPROPRIATE.
- 1 GATHER ALL EXCESS WIRE AFTER MAKING ALL CONNECTIONS AND BUNDLE
AND SECURE WITH TIE-WIRE 008343-01-000 OR 093147-01-000.

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-EXTERIOR LAMPS		
SHEET 2	PART NO 171037	REV



265 CODES/STANDARDS-CSA/CMVSS

1B1 CODES/STANDARDS USA

1B1 265



FIRST USED		
10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE:		
WIRING INSTL-EXTERIOR LAMPS		
SHEET 3	PART NO 171037	REV

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

KEY	PART NUMBER	U/M	DESCRIPTION
	097917-01-700	EA	LENS-LIGHT, CLEAR

097917-01-08A/09A
VENDOR NO.
30-78-021



J-SERIES

- 1LL FRTL(FRED) 27,000#-22.5 TIRE
- 70C RADIO - SATELLITE
- 579 RADIO - CB WIRE PREP
- 36N FANS-DEFROSTER, AUXILIARY
- 28K SUNVISORS - MANUAL (2)
- 28J SUNVISORS - POWERED (2)
- 193 TV ANTENNA-AMPLIFIED SYSTEM
- 15D GPS-NAVIGATION SYSTEM
- 15A DRIVER CONVENIENCE PACKAGE
- 12L DOOR-DRIVER
- 1PV WORKHORSE 24,000#-22.5 TIRE
- 1PS WORKHORSE 22,000#-22.5 TIRE
- 16Z FORD 24,000#-22.5 ALUM WHEEL
- 16L FORD 22,000#-22.5 AL WHL
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA
- 1B1 265







FIRST USED		
10 D,J,K-SER		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-FRONT END		
SHEET 5	PART NO. 169925	REV

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

NOTES:

1. WINNEBAGO WIRE ASSEMBLIES ARE SHOWN FOR CLARITY.



- | | |
|-----|-------------------------------|
| 1LL | FRTL(FRED) 27,000#-22.5 TIRE |
| 28J | SUNVISORS - POWERED (2) |
| 15A | DRIVER CONVENIENCE PACKAGE |
| 64Q | SEAT PED-6-WAY POWER DRIVER |
| 611 | WTR HTR-AUX AUTO/MOTORAID |
| 57M | LAMPS-FOG |
| 1B2 | WTR HTR-10GAL/ELEC/LP/MTRAIID |
| 1PV | WORKHORSE 24,000#-22.5 TIRE |
| 1PS | WORKHORSE 22,000#-22.5 TIRE |
| 16Z | FORD 24,000#-22.5 ALUM WHEEL |
| 16L | FORD 22,000#-22.5 AL WHL |
| 265 | CODES/STANDARDS-CSA/CMVSS |
| 1B1 | CODES/STANDARDS USA |

- 5 32H, 38N, 38T WITH 15A OR 28J
- 4 32H, 35P, 38N, 38T ONLY
- 3 CONNECT DDG TO HOLE IN BUSS BAR OR TO BOTTOM LUG OF 30 AMP BREAKER.
- 2 WORKHORSE PANEL SHOWN.
- 1 ALL CIRCUITS ARE IN WIRE ASM-IP,MAIN.

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

	FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000
---	--


FIRST USED		
10 D,J,K-SER		
DO NOT SCALE DRAWING		
TITLE:		
WIRING INSTL-FRONT END		
SHEET 6	PART NO	REV
	169925	

D

C


B

A



DETAIL GC 64Q

J-SERIES



VIEW GB
COURTESY CENTER
(CHASSIS SUPPLIED)

1PS 1PV

- 1LL FRTL(FRED) 27,000#-22.5 TIRE
- 64Q SEAT PED-6-WAY POWER DRIVER
- 611 WTR HTR-AUX AUTO/MOTORAID
- 60M HYDRAULIC LEVEL JACKS-AUTO
- 57M LAMPS-FOG
- 28X MIRRORS-EXTERIOR W/DEFROST
- 1B2 WTR HTR-10GAL/ELEC/LP/MTRAIID
- 1PV WORKHORSE 24,000#-22.5 TIRE
- 1PS WORKHORSE 22,000#-22.5 TIRE
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265


FIRST USED		
10 D,J,K-SER		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-FRONT END		
SHEET 7	PART NO 169925	REV

D

C

B

A



- 6 LEAVE 675±50MM OF WIRE PEDESTAL.
- 5 2009 FORD CHASSIS.
- 4 CONNECT CHASSIS SUPPLIED HOUSING LABELED "SEAT BELT BYPASS" TO POSITION D9 IN CONVENIENCE CENTER.
- 3 WIRING FROM LEVELING SYSTEM. SEE LEVELING SYSTEM INSTL. FOR ADDITIONAL INFORMATION.
- 2 CONNECT POSITIVE WIRE TO TERMINAL MARKED WITH A "+".
- 1 CHASSIS SUPPLIED



NOTES:

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000



FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

X-X

DETAIL GA



- 7 WITH SWITCH INSTALLED THIS SIDE OF SWITCH WILL FACE LEFT SIDEWALL.
- 6 DETAIL IS LOOKING AT SWITCH FROM THE BACK SIDE OF SWITCH AS ITS INSTALLED.
- 5 POSITIONS NOTED IN PARENTHESIS ARE LOCATIONS IN WORKHORSE SUPPLIED HOUSING.
- 4 REMOVE TERMINALS & TAPE BACK TO LOOM.
- 3 WITHOUT 36N
- 2 SEE DETAIL HC FOR ORIENTATION.
- 1 SEE DETAIL HD FOR ORIENTATION.



D,J-SERIES

- | | |
|-----|------------------------------|
| 1PV | WORKHORSE 24,000#-22.5 TIRE |
| 1PS | WORKHORSE 22,000#-22.5 TIRE |
| 1PR | WORKHORSE 22,000#-19.5 TIRE |
| 1LL | FRTL(FRED) 27,000#-22.5 TIRE |
| 16Z | FORD 24,000#-22.5 ALUM WHEEL |
| 16L | FORD 22,000#-22.5 AL WHL |
| 16K | FORD CHASSIS 22,000 |
| 265 | CODES/STANDARDS-CSA/CMVSS |
| 1B1 | CODES/STANDARDS USA |

- 1B1 265

10 D,J,K-SER

DO NOT SCALE DRAWING

TITLE: WIRING INSTL-FRONT END

SHEET 9	PART NO 169925	REV
---------	--------------------------	-----

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000

	FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000
---	--


- 3 ROUTE WIRES THROUGH HOLE IN STEEL.
- 2 MOUNT SENSOR OR SENSOR BRACKET TO HORIZONTAL TUBE ON FIBERGLASS AS SHOWN.

1. GATHER ALL EXCESS WIRE AFTER MAKING ALL CONNECTIONS. BUNDLE AND SECURE WITH WIRE TIE 008343-01-000 OR 093147-01-000.

NOTES:

091206-04-000			
KEY	PART NUMBER	U/M DESCRIPTION	VENDOR NO.
	091206-02-700	EA KNOB-INNER	66C-00019
	091206-02-701	EA KNOB-OUTER	66C-00020
	091206-04-700	EA SWITCH ASSEM. ONLY	250-6623
	102362-03-700	EA MODULE-WIPER CONT., DYNAMIC	66D-00093

J-SERIES
P-SERIES
R-SERIES
169847-04



- RADIO-AM/FM/CD
163142-15-000 (UP TO 09-06-09)
172120-05-000 (AFTER 09-07-09)
REMOTE CONTROL
163142-09-000 (UP TO 11-22-09)
172120-07-000 (AFTER 11-23-09)
REMOTE CONTROL
163142-13-000
REMOTE CONTROL
163142-10-000

HARNESS
172120-03-000 (AFTER 09-07-09)

RECEIVER-INFRARED
163142-11-000

- 7 FORD CHASSIS.
- 6 WORKHORSE AND FREIGHTLINER CHASSIS.
- 5 PLUG I-POD CABLE INTO LEAD ON BACK OF RADIO MARKED 'I-POD'.
ROUTE CABLE UP LEFT A-PILLAR AND INTO OVERHEAD CABINET
ABOVE DRIVER. LEAVE 600 MM OF CABLE IN OVERHEAD TIED UP
WITH WIRE TIE 8343-01-000.
- 4 INSTALL PER DRAWING 170205.
- 3 TO BE SUPPLIED LOOSE IN WINNEBAGO OWNERS CASE.
- 2 BEND TABS ON ALL 4 SIDES TO SECURE MOUNTING BRACKET TO DASH OPENING.
- 1 SUPPLIED WITH RADIO.

NOTES:

70C	RADIO - SATELLITE
19V	RADIO-AM/FM STEREO CD PLAYER
265	CODES/STANDARDS-CSA/CMVSS
1B1	CODES/STANDARDS USA

1B1 265 19V

10 J,P,R-SERIES

DO NOT SCALE DRAWING

TITLE:

PART NO

169847

11/3/2009

8	7
DRAWING NO.	MODEL
169917-01	J32H
169917-02	J35Z
169917-03	J37F
169917-04	J38N
169917-05	J35P
SHEETS	
1,6A,6B,6C	
2,7A,7B,9	
3,5A,5B,5C,8A,8B	
4,11A,11B,11C	
10,11A,11B,11C	

D

C


B

A

- 2 PARTS ARE SUPPLIED WITH SATELLITE KIT 154474-02-000.
- 1 SEE ROOF ASM FOR ADDITIONAL INFORMATION.

NOTES:

SWITCH-CONTROL
163598-02-000



SCREW
000G12-06-12U

DETAIL AA 78K

RECEPTACLE-BLANK
058707-02-000 (UP TO 01-24-10)
RECEPTACLE-BLANK
176158-01-01A (AFTER 01-25-10)
(DETAIL AB)

RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

265 LABEL
158542-02-01A

RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

RCP-B OVHD
(PUR-2)

FROM RCP-OVHD TO RCP FRONT RH
(WIRE IN SIDEWALL)

DETAIL AB

6

5



4

3

2

REF:

1

2/6/2010

CABLE ASM-SATELLITE
CONTROL FROM ROOF ASM

1JM SPEAKER
160868-01-000 (3)
GRILLE
160868-02-01A (3)
SCREW
000G11-08-08B (12)

FA 1JM

42K TV-32",FLAT PANEL LCD
169151-02-000(UP TO 05-03-09)
173556-01-000(AFTER 05-04-09)

3-PIN HOUSING
CONNECTS TO WIRE
WIRE ASM-ROOF

RJ-11 CONNECTOR IS TO
BE INSERTED INTO CONNECTOR
ON CONTROL SWITCH

HOME THEATER SYSTEM 1JM
164270-01-000(UP TO 05-03-09)
173514-01-000
(AFTER 05-04-09,UP TO 11-29-09)
173514-02-000(AFTER 11-30-09)
WIRE ASM-JUMPER,SPEAKER
153349-08-000(UP TO 05-03-09)
153349-01-000(AFTER 05-04-09)
FASTENER-DUAL LOCK
085774-01-000
085774-02-000

SATELLITE
RECEIVER (REF)

PLATE-WALL
149557-04-02A
SCREW
000G67-10-08B (2)

RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)
LABEL
158542-02-01A 265


RECEPTACLE-DOUBLE
172839-01-01A (UP TO 01-24-10)
RECEPTACLE-DOUBLE, FLUSH MOUNT
176149-01-01A (AFTER 01-25-10)
PLATE-COVER
176159-01-01A (AFTER 01-25-10)

CONTROL CENTER SWITCHING
142258-01-000
BRACKET-VIDEO SWITCH
156586-01-02B
SCREW
000G11-08-12B (4)

J32H

- 48R SAT TV SYSTEM IN-MOTION
- 42K TV-32" COLOR,STEREO W/REMOTE
- 78K SATELLITE DISH-AUTOMATIC
- 25F DIGITAL VIDEO DISC PLAYER
- 1JM HOME THEATER SOUND SYSTEM
- 1JF HOME THEATER SYS-WITHOUT
- 79H ENTERTAINMENT CTR-INTERIOR
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA

1B1 265 79H



COPYRIGHT 2010
WINNEBAGO
INDUSTRIES, INC.


DFTB	ORIG. DATE
CHGR	ALL DIMENSIONS ARE IN MILLIMETERS
P.E.	
M.E.	FIRST USED
DSNR	10 J-SERIES
UNSPECIFIED TOLERANCES ARE:	MATERIAL:
WHOLE DIM (X) ± 3	
ONE-PLACE (X.X) ± 1.5	
TWO-PLACE (X.XX) ± 0.50	
ANGLE ± 1°	
THIRD ANGLE PROJECTION	


DO NOT SCALE DRAWING

TITLE:	WIRING INSTL-TV/DVD
SHEET 1 OF 19	PART NO 169917
REV	

FOR
ELECTRICAL
CALLOUTS
SEE DWG NO.
121339-01-000

FOR ELECTRICAL
TORQUE
SPECIFICATIONS
SEE DWG NO.
128783-01-000





- 10 CONNECT ANTENNA CABLES TO DVD PLAYER AND MOUNT ANTENNAS AS HIGH AS POSSIBLE.
- 9 WITH 48R CABLES ARE CONNECTED TO THE SATELLITE CONTROL MODULE AS SHOWN BYPASSING THE ADAPTER, CABLE.
- 8 CABLE IS SUPPLIED WITH HOME THEATER RECEIVER.
- 7 ROUTE CABLE TO LEFT OVHD CABINET AND COIL EXCESS NEXT TO SATELLITE PREP PLATE.
- 6 SEE WIRING INSTL-BODY, 12V FOR ADDITIONAL INFORMATION
- 5 CONNECTED TO THE REAR SIDE OF SATELLITE PREP PLATE, CONNECTION LABELED 'FROM ROOF SATELLITE DISH.'
- 4 CONNECTED TO THE REAR SIDE OF SATELLITE PREP PLATE, CONNECTION LABELED 'FROM PORTABLE SATELLITE DISH.'
- 3 NOT USED WITH 48R
- 2 CABLE ROUTED IN ROOF OR THROUGH WIRE ASM-COACH.
- 1 CONNECTED TO THE REAR SIDE OF SATELLITE PREP PLATE, CONNECTION LABELED 'TO SATELLITE RECEIVER OUTPUT.'

NOTES:

- 78K SATELLITE DISH-AUTOMATIC
- 48R SAT SYS IN-MOTION W/O RCVR
- 1JM HOME THEATER SOUND SYSTEM
- 265 CODES/STANDARDS-CSA/CMVSS
- 1B1 CODES/STANDARDS USA


FIRST USED		
10 J-SERIES		
DO NOT SCALE DRAWING		
TITLE: WIRING INSTL-TV/DVD		
SHEET 6B	PART NO 169917	REV

J32H (AFTER 05-04-09, UP TO 11-29-09)

FOR ELECTRICAL TORQUE SPECIFICATIONS SEE DWG NO. 128783-01-000

FOR ELECTRICAL CALLOUTS SEE DWG NO. 121339-01-000

DETAIL FA



KEY	PART NUMBER	U/M	DESCRIPTION
	164270-01-700	EA	REMOTE

164270-01-000
VENDOR NO.
STS2891REM

KEY	PART NUMBER	U/M	DESCRIPTION
1	168408-01-700	EA	REMOTE

168408-01-000
VENDOR NO.
PSVCDV2007 SVC PK

KEY	PART NUMBER	U/M	DESCRIPTION
	169154-01-700	EA	REMOTE - TV

169151-01-000, 169151-02-000
VENDOR NO.
RRMCGA667WJSA

KEY	PART NUMBER	U/M	DESCRIPTION
	169154-01-700	EA	REMOTE - TV

169154-01-000
VENDOR NO.
RRMCGA667WJSA

KEY	PART NUMBER	U/M	DESCRIPTION	VENDOR NO.
	171727-01-700	EA	REMOTE	171727-01-000 PR7ATSC